




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁴ : H04Q 3/00		A1	(11) International Publication Number: WO 89/ 04578
			(43) International Publication Date: 18 May 1989 (18.05.89)
(21) International Application Number: PCT/US88/02390		(74) Agents: TAYLOR, Edwin, H. et al.: Blakely, Sokoloff, Taylor & Zafman, 12400 Wilshire Boulevard, Seventh Floor, Los Angeles, CA 90025 (US).	
(22) International Filing Date: 14 July 1988 (14.07.88)			
(31) Priority Application Number: 119,330		(81) Designated States: AT, AT (European patent), AU, BB, BE (European patent), BG, BR, CH, CH (European patent), DE, DE (European patent), DK, FI, FR (European patent), GB, GB (European patent), HU, IT (European patent), JP, KP, KR, LK, LU, LU (European patent), MC, MG, MW, NL, NL (European patent), NO, RO, SD, SE, SE (European patent), SU.	
(32) Priority Date: 10 November 1987 (10.11.87)			
(33) Priority Country: US			
(71) Applicant: ECHELON SYSTEMS [US/US]; 727 University Avenue, Los Gatos, CA 95030 (US).		Published <i>With a revised version of the international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>	
(72) Inventors: MARKKULA, Armas, C., Jr.; 250 Family Farm Road, Woodside, CA 94062 (US). SANDER, Wendell, B.; 112 Harwood Court, Los Gatos, CA 95032 (US). EVAN, Shabtai; 13648 Westover Drive, Saratoga, CA 95070 (US). SMITH, Stephen, B.; 611 Navarraq Drive, Scotts Valley, CA 95066 (US). TWITTY, William, B.; 141 Lance Court, Santa Cruz, CA 95065 (US).		Date of publication of the revised version of the international search report: 15 June 1989 (15.06.89)	

(54) Title: NETWORK AND INTELLIGENT CELL FOR PROVIDING SENSING, BIDIRECTIONAL COMMUNICATIONS AND CONTROL



(57) Abstract

A network for providing sensing, communications and control. In the present invention a plurality of intelligent cells (27, 28), each comprising an integrated circuit having a processor and input/output sections are coupled in a network. Each of the programmable cells includes a unique identification number (ID) at the time it is manufactured. When organized in a network, each of the cells performs at least one of the following functions: (1) sensing, (2) communicating, (3) controlling. Groups of cells may be organized to perform group functions and may be assigned a group ID. Cells and groups may be referenced by cell ID and group ID.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	FR	France	ML	Mali
AU	Australia	GA	Gabon	MR	Mauritania
BB	Barbados	GB	United Kingdom	MW	Malawi
BE	Belgium	HU	Hungary	NL	Netherlands
BG	Bulgaria	IT	Italy	NO	Norway
BJ	Benin	JP	Japan	RO	Romania
BR	Brazil	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic	KR	Republic of Korea	SE	Sweden
CG	Congo	LI	Liechtenstein	SN	Senegal
CH	Switzerland	LK	Sri Lanka	SU	Soviet Union
CM	Cameroon	LU	Luxembourg	TD	Chad
DE	Germany, Federal Republic of	MC	Monaco	TG	Togo
DK	Denmark	MG	Madagascar	US	United States of America
FI	Finland				

NETWORK AND INTELLIGENT CELL FOR PROVIDING SENSING,
BIDIRECTIONAL COMMUNICATIONS AND CONTROL

BACKGROUND OF THE INVENTION

1. Field of the Invention

The invention relates to the field of networks with distributed intelligence, configuration and control and intelligent
5 cells used in networks, primarily where the networks are used for sensing, communicating and controlling.

2. Prior Art.

There are many commercially available products which provide sensing, control and communications in a network
10 environment. These products range from very expensive, elaborate systems, to simple systems having little intelligence. As will be seen, the present invention is directed towards providing a system having a relatively large amount of intelligence and computational power but at a low cost.

15 One commercially available system "X-10" provides control, by way of example, between a light switch and a light. When the light switch is operated, a code pattern is transmitted over the power lines to a receiver at the light. The code pattern is transmitted twice, once in its true form and once in its
20 complementary form. When the code is received by the receiver, it is interpreted, and thereby used to control the light. Mechanical addressing means are employed to allow the

transmitter at the switch to communicate with the specific desired receiver at the light.

As will be seen, the present invention provides substantially more capability and flexibility than current
5 systems.

Applicant will submit prior art references on X-10 and other known prior art systems.

SUMMARY OF THE INVENTION

A network for providing sensing, communications and control is described. A plurality of intelligent cells each of which comprises an integrated circuit having a processor and input/output section are coupled to the network. Each of the programmable cells receives when manufactured a unique identification number (48 bits) which remains permanently within the cell. The cells can be coupled to different media such as power lines, twisted pair, radio frequency, infrared ultrasonic, optical coaxial, etc., to form a network.

Networks are distinguished from one another by system identification numbers (IDs). Groups of cells within each network are formed to perform particular functions and are identified by group IDs. Communications occur within the network through use of the system, group and cell IDs. Some cells (announcers) are assigned the task of sensing, for example, the condition of a switch, and others (listeners) the task of controlling, such as controlling a light. Cells can perform multiple tasks and be members of multiple groups, and, for example, can act as a repeater for one group and a listener in a another group. When manufactured, the cells are identical except for the cell ID; they

are programmed to perform specific tasks for a particular group or groups.

The preferred embodiment of the cell includes a multiprocessor and multiple I/O subsections where any of the processors can communicate with any of the I/O subsections. This permits the continual execution of a program without potential interruptions caused by interfacing with the I/O section. The I/O section includes programmable A-to-D and programmable D-to-A converters as well as other circuits for other modes of operation.

The network protocol provides great flexibility, and for instance, allows groups to be formed and/or changed after the cells are in place. As will be seen, the intelligence for the network is distributed among the cells. In general, the network is lightly loaded, although provisions are made for contention and other conditions which may arise. The communication between the cells in general is optimized for carrying out the functions assigned to groups, rather than for transmission of data unrelated to the control function of the network. For this reason, normally the packets carrying messages are relatively short compared to Ethernet, Arpa, AppleTalk, X-25 and many other broadband and data communication systems.

Other aspects of the invented network and cell will be apparent from the detailed description of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a block diagram illustrating typical application for the present invention.

Figure 2 is a diagram used to illustrate the grouping of
5 cells.

Figure 3 is another block diagram similar to Figure 2 used to illustrate the grouping of cells.

Figure 4 is a diagram used to describe subchannels.

Figure 5 is a diagram illustrating a plurality of cells; this
10 diagram is used to describe cell group formation employing the present invention.

Figure 6 is a chart illustrating the packet format used with the present invention.

Figure 7 is a chart illustrating the designation list portion
15 of the packet format of Figure 6.

Figure 8 illustrates a series of steps used in forming a group of cell with the present invention.

Figure 9 is a chart illustrating the code assignments for the three-of-six encoding used with the present invention.

20 Figure 10 is a block diagram of the communication and control cell.

Figure 11 is a block diagram of a portion of the instruction decoding logic used within the processor of the cell of Figure 10

Figure 12 is a detailed block diagram of the process of
5 **Figure 10**.

Figure 13 is a timing diagram for the processor of Figure 10; this diagram also shows latches and registers used to provide the pipelining employed by the cell.

Figure 14 is a block diagram illustrating the presently
10 preferred embodiment of the three-of-six encoder.

Figure 15 is a block diagram showing the presently preferred embodiment of the three-of-six decoder.

Figure 16 is a block diagram showing the presently preferred embodiment of the three-of-six code verifier.

15 **Figure 17** is an electrical schematic of the buffer section of one of the I/O sections.

Figure 18 is an electrical schematic of the counting and timing functions for an I/O subsection.

Figure 19 is an electrical schematic of the control and
20 state machine for an I/O section.

Figure 20 is an electrical schematic for the sample and hold means associated with the I/O subsections.

Figure 21. illustrates the network formed within an I/O subsection to do digital-to-analog conversion.

Figure 22 illustrates the network formed within an I/O section for analog-to-digital conversion.

5 Figure 23 is an electrical schematic showing the communications portion of an I/O subsection.

Figure 24 is a state diagram used for the I/O subsections and for transmission contentions.

Figure 25 is a state diagram for the link level ARQ.

10 Figure 26 is a state diagram for primary station connections.

Figure 27 is a state diagram for secondary station connections.

Figure 28 is a block diagram for a grouping device.

15 Figure 29 is a diagram showing the form in which the system ID is encoded for transmission by the packet and encoded within a cell.

Figure 30 is a diagram used to describe the operation of the input/output section and semaphore register.

DETAILED DESCRIPTION OF THE PRESENT INVENTION

An apparatus and method for providing a communications, sensing and control in a network is described. Where the network contains a plurality of intelligent cells, the cells in general are programmable single chip remote control, sensing and communication devices that, when interconnected (via various media) with other cells, have distributed sensing, communication, control and network configuration intelligence, configuration and control. The system comprises a network of cells organized in a hierarchy based on communications needs. Cells are organized into working "groups" independent of the network hierarchy. Groups of cells generally are used to perform a group function. This function is carried out by the assignment of tasks to cells within the groups. Cells communicate, control and sense information. In general, each cell has a unique identification number and perform information processing tasks such as: bidirectional communications protocol, input/output, packet processing and analog and digital sensing and control. In general, the system comprised of the cells has the characteristic of storing network configuring information that is distributed throughout the system; and communicates automatically routed messages among cells. Each system also has a unique

identification (ID) which in the presently preferred embodiment is 48 bits. Moreover, it contains versatile programmable input/output I/O circuits with digital versatile programming to configure cells to specific sensing, communication, control and I/O, analog I/O, communication I/O and communications bit rate sensing.

In the following description, numerous specific details are set forth such as specific frequencies, etc., in order to provide a thorough understanding of the present invention. It will be obvious, however, to one skilled in the art that these details are not required to practice the invention. In other instances, well-known circuits, methods and the like are not set forth in detail in order not to unnecessarily obscure the present invention.

I.

OVERVIEW OF AN APPLICATION OF THE PRESENT INVENTION

Before describing the present invention in detail, an understanding of a typical application will aid in appreciation of the details to follow. In Figure 1, a simple, typical application is shown based on the use of the present invention in a home. In

Figure 1, the switch 22 is used through the present invention to control the light 23.

The arrangement 20 comprises a cell 27 which is connected to the switch 22. The cell is also connected to a transceiver 29
5 which couples data onto the lines 24 and 25. Power for the transceiver and cell are provided from the power supply 30 which receives power from the lines 24 and 25. For this example, the lines 24 and 25 are ordinary household wiring (e.g., 110VAC) and the power supply 30, a five volt DC supply. The cell 27 is
10 preferably an integrated circuit which is described in more detail beginning with Figure 10. The transceiver 29 may be any one of many well-known devices for receiving and transmitting digital data and as presently contemplated does not perform any processing on transmitted data. The entire arrangement 20 may
15 be small enough to fit within an ordinary wallmounted electrical box which normally contains an electrical switch.

The arrangement 21 again may be small enough to fit within a typical electrical outlet box and includes a power supply 31 and transceiver 33 which may be identical in construction to the
20 power supply 30 and transceiver 29, respectively. This cell 28 is coupled to the transceiver 30 and power supply 29 as well as the solenoid operated power switch 32. Cell 28 may be identical to

becomes for practical purposes, or no matter how many networks are interconnected. The grouping device then accesses the individual cell IDs and assigns a system ID to each cell. In addition, the grouping device configures the cells into groups to
5 perform group related functions.

For the illustration of Figure 1, cell 27 is designated as "A" to indicate that its primary function is to "announce" that is, transmit the state of switch 22 on the network communications lines 24 and 25, and 34 and 35. On the other hand, cell 28 is
10 designated with the letter "L" since its primary function in Figure 1 is to "listen" to the network and in particular to listen to messages from cell 27. In subsequent figures, the "A" and "L" designations are used, particularly in connection with a group formation of multiple cells to indicate an announcer arrangement,
15 such as arrangement 20 and a listener arrangement, such as arrangement 21. For purposes of discussion the cells themselves are sometimes referred to as transmitting or receiving data without reference to transceivers. (In some cases, the transceivers may be a simple passive network or simple wires,
20 which couple the input/output of a cell onto a line. As will be seen the I/O section of the cells can provide output signals that

can drive a twisted pair or the like. Thus the cells themselves can function as a transceiver for some media.)

The cells 27 and 28 as will be described subsequently are processors having multiprocessor attributes. They may be
5 programmed prior to or after installing to perform their required function, such as an announcer or listener and for grouping combinations.

II.

NETWORK ORGANIZATION AND DEFINITIONS.

A. Definitions

5 Cell: A cell is an intelligent, programmable element or elements providing remote control, sensing and/or communications, that when interconnected with other like elements form a communications, control and sensing network or system with distributed intelligence.

10 Announcer: An announcer is a source of group messages.

Listener: A listener is a sink of group messages.

(An announcer in some cases may request state information from a listener.)

Repeater: A repeater is a cell which in addition to other
15 functions reads packets from a medium and rebroadcasts them.

Group: A set of cells which work together for a common function (for example, a switch controlling a set of lights) is referred to as a "group".

 In Figure 2, the group 37 has an announcer 37a, listeners
20 37b, and 37c, and a listener 40. A group 38 includes an announcer 38a, listeners 38b and 38c and the listener 40. Figure 2 illustrates that a single cell (cell 40) may be a listener in two

groups. If announcer 37a has a light switch function, it can control lights through cells 37b, 37c and 40. Similarly, a switch associated with announcer 38a can control lights through cells 37c, 37b, and 40.

5 In Figure 3, a group 42 includes announcers 44, 45 and listeners 46 and 47. The group 43 shares cell 44 with group 42; however, cell 44 is a listener for group 43. The group 41 shares cell 47 with group 42; cell 47 is an announcer for group 41 and for example, can announce to the listener 48 of group 41. Cell 47 also
10 operates as a listener for group 42. A single cell as shown may be an announcer for one group and a listener for another group (cells are programmed to perform these functions, as will be discussed). However, as presently contemplated, a single cell cannot announce for more than one group.

15 (In the currently preferred embodiment each cell has three input/output pairs of lines and a select line. Each pair shares a common set of resources. The lines may be used independently for some functions where the required shared resources do not conflict. In other functions, the lines are used as pairs. In this
20 example, a pair of leads from cell 27 are coupled to a light switch and another pair are used for communications from the announcer, cell 27.)

Subchannel: In Figure 4, a first plurality of cells are shown communicating through a common medium such as a twisted pair 50 (cells are shown as "C", announcers as "A" and listeners as "L"). This (e.g., twisted pair 50) is defined as a subchannel, that is, a set of cells all of which communicate directly with one another over the same medium. A broadcast by any member of the subchannel, such as the cell 49, will be heard by all members of that subchannel over the twisted pair 50.

Channel: A channel comprises two or more subchannels where all the cells communicate using the same medium. In Figure 4, another plurality of cells are shown coupled to twisted pair 52 forming another subchannel. Assume cells 56 and 57 communicate between one another through a twisted pair 72. They form yet another subchannel. The cells associated with the twisted pairs 50, 52 and 72 comprise a single channel. It is possible that the twisted pairs 50, 52 and 72 are one continuous twisted pair with one subchannel 50 so far apart from the second subchannel 52 that the only communications between subchannels is over the portion of the twisted pair 72 running between cells 56 and 57. In this case the cells 56 and 57 are assigned to be "repeaters" in addition to whatever other function they may serve (e.g., announcer or listener).

A group 55 is illustrated in Figure 4 which comprises an announcer and listener in the two different subchannels. Another group 75 is illustrated comprising an announcer on one subchannel 51 and subchannel 52, where the subchannels are not part of the same channels since they use different media.

Gateway: A gateway reads packets from two different media and rebroadcasts them. A cell may be a gateway.

Communications between channels is through gateway 54.

In Figure 4, an additional subchannel which includes the cell 58 is coupled to another medium 51, for example, a common power line. The cell 58 is shown connected to channel gateway 54 which in turn communicates with the twisted pair 52. The gateway 54 does not necessarily perform either an announcer or listener function, but rather for the illustrated embodiment, performs only a channel gateway function by providing communication between two different media.

Subnetwork: A subnetwork comprises all the cells having the same system identification (system ID). For example, all the cells in a single family home may have the same system ID. Therefore, the channels of Figure 4 may be part of the same subnetwork in that they share the same system ID.

Full Network: A full network may comprise a plurality of subnetworks each of which has a different system ID; a communications processor is used for exchanging packets between subnetworks. The communications processor translates packets changing their system ID, addressing and other information. Two factory buildings may each have their own system ID, but control between the two is used by changing system IDs. (The word "network" is used in this application in its more general sense and therefore refers to other than a "full network" as defined in this paragraph.)

Other terms used later are:

Probe Packet: A packet routed by flooding which accumulates routing information as it travels through the network.

Grouping Device: A device that controls determination of routes among cells, assigns cells to groups, and assigns function to group members.

Contention: The state which exists when two or more cells attempt to transmit a broadcast on the same subchannel at the same time and their signals interfere.

B. GROUP FORMATION

1. Cells Assigned to a group by a postinstallation grouping device.

Assume that the plurality of cells shown in Figure 5 are all
5 connected to communicate over the power lines in a home and are
part of the same channel. Further assume that one cell, announcer
60, is to be grouped with the listener 65. The lines between the
cells such as line 59 is used to indicate which of the cells can
communicate directly with one another, for instance, announcer
10 60 and cell 61 can communicate with one another. (Cells 61, 62,
63, 64 and 66 of course may be announcers or listeners in other
groups, but for purposes of explanation are shown as "C" in Figure
5.) Since announcer 60 and cells 61, 62, and 63 all communicate
with one another, they are on the same subchannel. Similarly,
15 cells 62, 64, 65 and 66 are another subchannel. (There are other
subchannels in Figure 5). Importantly, however, announcer 60 and
listener 65 are in different subchannels of the channel of Figure 5
and there are numerous routes by which a message can be passed
from announcer 60 to listener 65, for example, through cells 61
20 and 64 or through cells 62 and 64, etc.

Note that even though all the cells are on the same power
system of a house, they may not communicate directly with one

another. For instance, the announcer 60 may be on one circuit which is only coupled to the listener 65 through long lengths of wire running the length of a home and a low impedance bus bar of a circuit breaker panel. The high frequency communication
5 messages may be sufficiently attenuated through this path to prevent direct communications between cells even though they are physically close to one another.

For the following description, it is assumed that each of the cells can broadcast without interfering with the broadcast of
10 other cells. That is, messages do not interfere with one another. The case where some contention occurs is dealt with under the protocol section of this application.

In one embodiment, the group of announcer 60 and listener 65 is formed by using the grouping device shown in Figure 28.
15 Note that before this group is formed the announcer 60 and listener 65 are ordinary cells, not designated to be an announcer and listener. Each grouping device may be assigned a unique 48 bit system ID at time of manufacture (in the presently preferred embodiment a 48 bit number is used). In the presently preferred
20 embodiment, a cell is included with each grouping device. The cell's ID becomes the system ID. This assures that each system has a unique system ID. By way of example, each home has its

own "grouping" device and hence, its own system ID for the subnetworks used in the home. This system ID is used in cell packets for the subnetwork. In this example, the grouping device has available the cell IDs of cells 60 and 65. (Various methods of
5 obtaining cell IDs will be described later.)

The grouping device is connected to cell 60 by communicating through one of its three pairs of input/output (I/O) lines of the cell (or the select pin) and the grouping device reads the 48 bit ID number of the cell 60. (Different methods of
10 determining the cell's IDs are described in the next section.) The grouping device next generates a random bit binary number which in the presently preferred embodiment is 10 bits. This number functions as a group identification number (also referred to as the group address) for the group comprising the announcer 60 and
15 listener 65. The grouping device checks this number against other group IDs which it has previously assigned to determine if the group ID has previously been used. If it has been already used it generates another number. (A single grouping device, for instance keeps track of all the group IDs assigned in a single
20 home.) The grouping device programs the cell 60 designating it as an announcer.

The grouping device may cause the announcer 60 to broadcast the group number in a special packet which asks all cells in the network to acknowledge the message if they have been designated as a member of this group. This is another way
5 to verify that the group ID has not been used.

The grouping device now determines the ID number of the cell 65. This may be done by connecting the grouping device directly to the cell 65 even before the cell is installed or by other methods discussed in the next section. (A cell and a group
10 can be assigned ASCII names, for example, "porchlight" (cell name) and "exterior lights" (group name). This is used to allow selection of cell IDs or group IDs by accessing the ASCII name.

Now the grouping device causes the announcer 60 to transmit a probe packet. The probe packet contains the ID of cell
15 65. The packet directs all cells receiving the packet to repeat it and directs cell 65 to acknowledge the packet. Each cell receiving the probe packet repeats it and adds to the repeated packet its own ID number. Each cell only repeats the packet once (the mechanism for preventing a probe packet from being repeated
20 more than once is described later.)

The cell 65 receives the probe packet through numerous routes, including those which in the diagram appear to be most

direct (via cell 62) and those which are longer, for example, via cells 61 and 64. It is assumed that the first probe packet to arrive at cell 65 took the most direct route and is therefore the preferred routing. (Assume that this is via cell 62.) Cell 65
5 receives a packet which indicates that the probe packet was transmitted by cell 60, repeated by cell 62 and intended for cell 65. The other probe packets received by cell 65 after this first packet are discarded by cell 65.

Cell 65 now transmits an acknowledgement back to
10 announcer 60. This packet includes the routing of the probe packet (e.g., repeated by cell 62). The packet directs cell 62 to repeat the packet to confirm its receipt.

After announcer 60 receives the acknowledgement packet for cell 65 it determines that cell 62 must be a repeater. The
15 grouping device causes announcer 60 to send a repeater assignment packet which includes the unique ID number of cell 62, the group number and a message which informs cell 62 that it is assigned a repeater function for the group. This causes cell 62 to repeat all those packets for the group comprising announcer
20 cell 60 and 65. Another message is sent from announcer 60 under control of the grouping device repeated by cell 62, designating cell 65 as a listener, causing it to act upon messages for the

group (cell 65 becomes a group member.) The grouping device assigns members a member number which is stored by member cells.

The group formation described above is shown in Figure 8 by steps or blocks 68 through 72. Block 68 illustrates the broadcasting of the probe packet (e.g., cell 60 transmits the initial probe packet to all cells). The packet includes the address of a destination cell. As the packet proceeds through the network, the packet accumulates the ID numbers of those cells repeating the packet (block 69). Block 70 shows the acknowledgement (reply) to the probe packet from the destination cell (e.g., cell 65). This packet returns the ID numbers of the repeaters contained in the first received probe packet. Repeater assignment packets are sent out by the announcer causing each repeater to rebroadcast packets for the group; this is shown by block 71. Finally, as shown by block 72, the destination cell such as cell 65 is designated as a listener.

2. Cells assigned to a group by a preinstallation grouping device.

There may be several types of preinstallation grouping devices, for example, see Figure 28 for a device which may be used. One type is a device that a manufacturer uses to preassign cells to groups. Another type of preinstallation grouping device

is one that a retailer or other cell vendor may use to assign cells to groups before installation.

A grouping device assigns a cell to a group and assigns the cell's function(s) for that group. The grouping device may also
5 assign a system ID to the cell. The system ID assigned by a preinstallation grouping device is not necessarily a unique system ID. (Postinstallation grouping devices assign a unique system ID to each system.)

One method that may be used by preinstallation grouping
10 devices to generate a system ID is to choose a system ID from a range of the 48 bit address and system ID numbers that have been set aside for use as preinstallation system IDs. Just as the cell IDs in the range 1-1023 have been set aside for use as group IDs and group addresses, the cell IDs in the range 1024-2047 can be
15 set aside for use as preinstallation system IDs.

It is desirable that grouping devices and other network control devices be able to identify preinstallation system IDs as opposed to postinstallation system IDs. Since postinstallation system IDs are generated by copying a cell ID, cell IDs should not
20 be assigned in the range set aside for preinstallation system IDs. Therefore, ID numbers in that range would not be assigned to cells as cell IDs.

Cells may be sold in sets that have been preassigned to a group by the manufacturer. The type of preinstallation grouping device used by the manufacturer assigns cells to groups by writing the appropriate codes into the cells' nonvolatile memory.

- 5 The user may install such a set of cells and it will operate without assignment by a postinstallation grouping device provided that the set of cells may communicate via a single subchannel.

- 10 A user may assign cells to a group at the time cells are purchased or at any other time before installation. Such cells, unlike the case previously discussed, are not assigned to groups by the manufacturer and are called unassigned cells. Unassigned cells all have the same system ID, a system ID number that has been set aside for use only by unassigned cells.

- 15 The user assigns a set of cells to a group by using a preinstallation grouping device that may be different from the preinstallation grouping device used by a manufacturer.

- 20 Typically, such a grouping device will operate on one cell at a time. The operator commands the grouping device to generate a new group ID and system ID and then each cell is connected to the device in turn. The operator commands the grouping device to assign a cell to the group while the cell is connected to the

grouping device. The grouping device assigns cells the same group ID and system ID until it is commanded by the operator to generate a new group ID and system ID.

The user may install such a set of cells and it will operate without use of a postinstallation grouping device provided that the set of cells can communicate via a single subchannel.

3. Unassigned Cells Grouping and Self-Assignment After Installation.

Unassigned cells may create a group and assign themselves to the group after installation in the following manner.

The first announcer cell that is stimulated via its sensor input (e.g., light switch) controls the group formation process. It chooses a system ID number at random from the range of system ID numbers that have been set aside for preinstallation grouping devices. It chooses a group ID number at random. It then broadcasts the group ID number in a packet that requests a reply from any cells that are members of that group. If the transmitting cell receives any such replies, it chooses another group ID at random. The cell continues this process of selecting a random group ID and testing to see if it is already in use until it finds a group ID that is unused in the system in which it is operating.

An unassigned cell's default configuration information programmed at the factory identifies its function as either a listener or an announcer. If the unassigned cell is an announcer, it waits for its sensing input to be stimulated, and when it is
5 stimulated, the cell transmits a packet addressed to a group.

If an unassigned cell is a listener, it listens after power-up for a packet. The cell takes the group ID from the first packet it receives and assigns itself to that group. The cell then sends a reply to the announcer cell. This reply is not an acknowledgement
10 only packet; it is a packet that identifies the cell as a listener in the group and the packet must be acknowledged by the announcer. This assures that all of the listener identification packets will arrive at the announcer even though there will be contention and collisions in the process.

15 The cell that transmitted the group announcement builds a list of group members as each reply comes in. It then sends a packet to each listener assigning that listener a group member number.

4. Unassigned Cells Joining Preexisting Group After Installation.

20 Unassigned cells may be added to existing systems and assigned to a group in a manner similar to the above method

discussed in Section 3 above. A listener joins the system and a group by the same method as in Section 3 above.

In the above example, the announcer waits to be stimulated via its sensor input. An unassigned announcer waits for its first
5 sensor input stimulation or its first received packet. Of those two events, the event that occurs first determines the subsequent actions of the announcer cell.

If the cell is stimulated first, it controls a group formation process just as in the above example. If the announcer cell
10 receives a group packet first, it joins that group as an announcer. It then sends a packet to the group announcer requesting configuration information about the group (group size, number of announcers, etc.) and the assignment of a group member number.

C. METHODS OF IDENTIFYING A CELL FOR GROUPING

In order for a grouping device to go through the steps necessary to form a group or add a cell to a group, it must know the IDs of the cells to be added to the group. The grouping device
5 then uses those cell IDs to address commands to the cells during the grouping process. The methods that a user with a grouping device may use to obtain the cell IDs are listed below. Note that a grouping device or other control device's ability to communicate with a cell in the following example may be limited by security
10 procedures if used. The security procedures, limitations on communications and levels of security are not critical to the present invention. The following example assumes that no security procedures are in place. In particular, it may be impossible for a grouping device to communicate with installed
15 cells unless the grouping device has the system key (system ID and encryption keys.)

1. Direct connection to the cell.

The grouping device may be connected to an I/O line of the cell package and then send a message to the cell requesting its ID.
20 Physical connection can be used to find a cell's ID either before or after the cell is installed. Known means can be used (e.g., a fuse

or a programmed disable command) to allow a user to disable this function in an installed cell to protect the security of the system.

2. Selection of the Cell Through Use of Special Pin

The user may use the grouping device or some other
5 selection device to physically select the cell by stimulating a cell input pin that has been designated to serve the selection function. The grouping device communicates with the cell through the normal communications channels and sends a broadcast message requesting that all selected cells reply with
10 their ID. Only one cell is selected so only that cell will reply to the request. Physical selection can be used to find a cell's ID either before or after the cell is installed. Again, a means can be provided to allow a user to disable this feature to protect the security of the system.

15 3. Query All Names of Previously Grouped Cells

It is assumed in this example that ASCII "groups" and "cell" names have been previously assigned to the cells. For this method, the grouping device queries all of the cells in a system to report their group and cell names (ASCII name). The user scrolls
20 through the list of group names by using the grouping device. The user selects the name of the group that is believed to contain the target cell. The grouping device displays the names of all of the

cells that are in the group and their assigned tasks (announcer, listener, repeater). The user selects the name of the cell that is believed to be the target cell.

If the selected cell is an announcer, the grouping device
5 prompts the user to activate the announcer by stimulating its input. For example; if the cell is attached to a light switch, the user turns the switch on and off. The cell sends announcement packets to the group. The grouping device listens to the communications channel and discovers the group and member
10 numbers or other codes of the activated announcer.

If the selected cell is a listener cell, the grouping device sends packets to the cell (using the group and member numbers for addressing) commanding it to toggle its output. For example, if the cell controls a light, the light will flash on and off. This
15 allows the user to verify that he has selected the correct cell.

The grouping device sends a packet (using group and member numbers for addressing) to the target cell with a command for the target cell to return its cell ID. The grouping device now knows the target ID and can proceed with the group assignment
20 process.

Querying names is used to find a cell's ID before or after the cell is installed.

4. Stimulate Group.

This method is used in a network in which group and cell ASCII names have been assigned. The user commands the grouping device to wait for the next group announcement. Then the user
5 stimulates the announcer in the group of interest. For example, if the announcer is a light switch, the user throws the switch. The grouping device hears the announcement packet and extracts the group ID from it.

The user may verify that this group ID is for the desired
10 group by causing the grouping device to send packets to all of the group listeners commanding them to toggle their outputs. The user verifies that it is the desired group by observing the actions of the listener cells (for example, if the group consists of lighting controls, the light flashes).

15 Now using that group ID, the grouping device broadcasts a packet to the group requesting that each cell reply with its cell name until the cell of interest is found. The user selects that name and the grouping device, knowing that cell's ID, can proceed with the group assignment process.

20 If a user elects, the ID of the cell may be verified before proceeding with the grouping procedure. The following procedure is used to verify that the ID is for the target cell.

If the selected cell is an announcer, the grouping device prompts the user to activate the announcer by stimulating its input. For example: if the cell is attached to a light switch, the user turns the switch on and off. The grouping device is then able
5 to discover the group address and member number of the cell.

If the selected cell is a listener, the grouping device sends packets to the cell (using the group and member numbers, for addressing) commanding it to toggle its output. For example, if the cell controls a light, the light will flash on and off. This
10 allows the user to verify that he has selected the correct cell.

5. Stimulate Announcer.

This method is used in a network in which no group or cell ASCII names have been assigned but announcers and listeners have been assigned. The grouping device sends a packet to all
15 cells in the network commanding each announcer to broadcast a packet containing its ID the next time it is stimulated. The grouping device then prompts the user to stimulate the announcer by activating its sensed device; for instance, turn on a light switch for a light switch announcer. Since the user will
20 stimulate only one announcer, the grouping device will receive only one packet with a cell ID.

There is a chance that another announcer cell will be stimulated at the same time. Perhaps someone else throws a light switch or a temperature sensor detects a temperature change. The user may want to verify that the ID received is for the correct cell. To verify that the cell ID is the correct one, the user goes through the announcer stimulation process a second time and verifies that the same results occur.

6. Toggle Listener

This method is used in a network in which no group or cell names have been assigned. The grouping device broadcasts a packet that queries cells that are listeners to reply with their ID. The grouping device needs to limit the number of cells replying so the packet contains an ID bit mask to limit replies to a subset of the possible cell IDs. When the grouping device has developed a list of listener IDs, it allows the user to toggle each listener, causing the listener cell to turn its output on and off. The user continues through the list of listener cells until he observes the target cell toggling its output. The user has then identified the cell to the grouping device and it can proceed with the grouping operation.

D. PACKET FORMAT

Each packet transmitted by a cell contains numerous fields. For example, a format used for group announcements is shown in Figure 6. Other packet formats are set forth in Appendix A.

- 5 Each packet begins with a preamble used for synchronizing the receiving cells' input circuitry (bit synch). The particular preamble code used in the currently preferred embodiment is described as part of the three-of-six combinatorial codes (Figure 9). A flag field of 6 bits begins and ends each of the packets. The
10 flag field code is also described in Figure 9.

- As currently preferred, each of the cells reads-in the entire packet, does a cyclic redundancy code (CRC) calculation on the packet except for the contention timer field and compares that result with the CRC field of the received packet. The ALU 102 of
15 Figure 12 has hardware for calculating the packet CRC and CRC registers 130 for storing intermediate results. If the packet CRC cannot be verified for an incoming packet, the packet is discarded. The packet CRC field is 16 bits as calculated, then converted into 24 bit fields for transmission in a 3-of-6 code
20 using the encoding of Figure 9. (For the remainder of discussion of packet fields in this section, the field length is described prior to encoding with the 3-of-6 combinatorial codes of Figure 9.) In

the currently preferred embodiment the CRC is a CCITT standard algorithm

$$(X^{16} + X^{12} + X^5 + 1).$$

The system ID is a 32 bit field as currently preferred. The
5 other 16 bits of the 48 bit system ID are included in the CRC calculation but not transmitted as part of the packet (Figure 29).

The link address field is a 48 bit field. When this field is all zeroes the packet is interpreted as a system wide broadcast which is acted upon by all the cells. For instance, a probe packet
10 has an all zero field for the link address. Group addresses are contained within the link address. For group addresses the first 38 bits are zero and the remaining 10 bits contain the group address. (The cell ID numbers assigned at the factory mentioned earlier range from 1024 to 2⁴⁸ since 2¹⁰ addresses are reserved
15 for groups.) The link address, in some cases, is an individual's cell's address. (For example, when a cell is being assigned the task of repeater or listener.)

The contention timer is a 10 bit field with an additional 6 bits for a CRC field (or other check sum) used to verify the 10
20 bits of the timer field. Each cell which repeats a packet operates upon this field if the cell must wait to transmit the packet. If packets are being transmitted by other cells a cell must wait to

transmit its packet, the time it waits is indicated by counting down the contention timer field. The rate at which this field is counted down can be programmed in a cell and this rate is a function of the type of network. The field starts with a constant
5 which may be selected by the type of network. Each cell repeating the packet counts down from the number in the field at the time the packet is received. Therefore, if a packet is repeated four times and if each of the four cells involved wait for transmitting, the number in the contention field reflects the sum
10 of the times waited subtracted from a constant (e.g., all ones). When the contention timer field reaches all zeroes, the cell waiting to transmit the packet discards the packet rather than transmit it. This prevents older packets from arriving and being interpreted as being a new packet.

15 As mentioned, the contention timer has its own 6 bit CRC field. If the contention timer field were included in the packet CRC, the packet CRC could not be computed until a packet could actually be transmitted. This would require many calculations in the last few microseconds before a transmission. To avoid this
20 problem a separate CRC field is used for the contention timer field. If the contention timer field cannot be verified by its 6-bit CRC, the packet is discarded.

The hop count field records the number of hops or retransmissions that a packet takes before arriving at its destination. This 4 bit field starts with a number which is the maximum number of retransmissions allowed for a particular packet and is decremented by each cell repeating a packet. For example, in a packet originated by a group announcer the starting "hop" count is the maximum number of retransmissions that the packet must undergo to reach all of the cells in a group. When this field becomes all zeroes, the packet is discarded by the cell, rather than being retransmitted. Therefore, 16 hops or retransmissions is the limit as currently implemented.

The link control field provides the link protocol and consists of 8 bits. This field is discussed in a subsequent section covering other layers of the protocol.

The random/pseudo random number field contains an 8 bit random number which is generated for each packet by the cell originally transmitting the packet. This number is not regenerated when a packet is repeated. This number is used as will be explained in conjunction with Figure 8 to limit rebroadcasting of probe packets; it also may be used in conjunction with encryption where the entire packet is to be encrypted.

The network control field (4 bits) indicates routing type or packet type, for instance, network control, group message, probe message, etc.

5 The source address field (variable size) contains, by way of example, the 48 bit ID number of the cell originating a packet. For a probe packet this field contains the ID number of the announcer. For an acknowledgement the field contains the ID of the listener. For a packet addressed to a group, this field contains the source cell's group member number.

10 The destination list is described in conjunction with Figure 7.

The message field is variable in length and contains the particular message being transmitted by the packet. Typical messages are contained in Appendix B. In the case of a probe
15 packet the field includes the routing; that is, each cell repeating includes its ID number to this field. The messages, once a group is formed, will, for instance, be used by announcer 60 to tell listener 65 to turn-on a light, etc.

20 The encryption field, when used, contains 16 bits used to verify the authenticity of an encrypted packet typically this portion of a packet is not changed when a packet is repeated. Well-known encryption techniques may be used.

The bracket 99 of Figure 6 represents the portion of a packet which remains unaltered when a packet is repeated. These fields are used to limit repeating as will be described in conjunction with Figure 8.

5 The destination list field of the packet of Figure 6 is shown in Figure 7. The destination list begins with a 4 bit field which indicates the number of members in a group designated to receive a message in the packet. Therefore the packet can be directed to up to 16 members of a group. The number of each of the members
10 within the group is then transmitted in subsequent 8 bit fields. The group number contained in the link address and member number contained in the destination list forms an address used to convey messages once the group is formed. If the destination number is zero, the packet is addressed to all members of the
15 group. For some packet types this field contains the ID of the receiving cell (see Appendix A).

E. MECHANISM FOR PREVENTING REBROADCASTING OF CERTAIN PACKETS

20

As previously mentioned, the probe packets are repeated only once by each of the cells after the packet is initially

broadcast. A special mechanism programmed into each of the cells allows the cells to recognize packets which it has recently repeated.

First, it should be recalled that as each cell transmits, or
5 retransmits a packet, it calculates a packet CRC field which precedes the end flag. For packets that are repeated, a new CRC is needed since at least the hop count will change, requiring a new packet CRC field for the packet. This CRC field is different from the CRC field discussed in the next paragraph.

10 As each packet requiring repeating is received, a repeater CRC number is calculated for the fields extending from the beginning of the link control to the end of the destination list as indicated by bracket 99 of Figure 6. As a cell rebroadcasts a packet it stores the 16 bit repeater CRC results in a circular list
15 of such numbers if the same number is not already stored. However, the packet is repeated only if the circular list does not contain the repeater CRC results calculated for the field 99.

Therefore, as each packet is received which requires repeating, the CRC is computed for the field 99. This is shown by
20 block 73a of Figure 8. This number is compared with a list of 8 numbers stored within the RAM contained within the cell indicated by block 73b. If the number is not found within the

stored numbers, the new repeater CRC results are stored as indicated by block 73c and the packet is repeated. On the other hand, if the number is found then the packet is not repeated. As presently implemented, 8 numbers are stored in a circular list, that is, the oldest numbers are discarded as new ones are computed.

The use of the repeater CRC calculation associated with the field 99 and the use of the circular list will prevent repeating of a previously rebroadcasted packet. Note that even if an announcer continually rebroadcasts the same sequence of messages, for example, as would occur with the continuous turning on and turning off of a light, a cell designated as a repeater will rebroadcast the same message since the packet containing messages appears to be different. This is true because the random number sent with each of the identical messages will presumably be different. However, in the instance where a cell receives the same message included within the same field 99 (same random number), the packet with its message will not be rebroadcast. This is particularly true for probe packets. Thus, for the establishment of groups discussed above, the broadcast probe packets quickly "die out" in the network, otherwise they may echo

for some period of time, causing unnecessary traffic in the network.

F. THREE-OF-SIX-COMBINATORIAL CODING

In many networks using the synchronous transmission of digital data, encoding is employed to embed timing information within the data stream. One widely used encoding method is Manchester coding. Manchester or other coding may be used to encode the packets described above, however, the coding described below is presently preferred.

10 A three-of-six combinatorial coding is used to encode data for transmission in the presently preferred embodiment. All data is grouped into 4 bit nibbles and for each such nibble, six bits are transmitted. These six bits always have three ones and three zeroes. The transmission of three ones and three zeroes in some combination in every six bits allows the input circuitry of the cells to quickly become synchronized (bit synch) and to become byte synchronized as will be discussed in connection with the I/O section. Also once synchronized (out of hunt mode) the transitions in the incoming bit stream are used to maintain synch.

20 The righthand column of Figure 9 lists the 20 possible combinations of 6 bit patterns where 3 of the bits are ones and 3 are zeroes. In the lefthand column, the corresponding 4 bit

pattern assigned to the three-of-six pattern is shown. For example, if the cell is to transmit the nibble 0111, it is converted to the bit segment 010011 before being transmitted. Similarly, 0000 is converted to 011010 before being transmitted.

- 5 When a cell receives the 6 bit patterns, it converts them back to the corresponding 4 bit patterns.

There are 20 three-of-six patterns and only 16 possible 4 bit combinations. Therefore, four three-of-six patterns do not have corresponding 4 bit pattern assignments. The three-of-six
10 pattern 010101 is used as a preamble for all packets. The flags for all packets are 101010. The preamble and flag patterns are particularly good for use by the input circuitry to establish data synchronization since they have repeated transitions at the basic data rate. The two three-of-six patterns not assigned can be used
15 for special conditions and instructions.

Accordingly, a cell prepares a packet generally in integral number of bytes and each nibble is assigned a 6 bit pattern before transmission. The preamble and flags are then added. The circuitry for converting from the 4 bit pattern to the 6 bit
20 patterns and conversely, for converting from the 6 bit patterns to the 4 bit patterns is shown in Figures 14 and 15.

III.

COMMUNICATION AND CONTROL CELL

A. Overview of the Cell

5

Referring to Figure 10, each cell includes a multiprocessor 100, input/output section 107-110, memory 115 and associated timing circuits shown specifically as oscillator 112, and timing generator 111. Also shown is a voltage pump 116 used with the memory 115. This cell is realized with ordinary integrated circuits. By way of example, the multiprocessor 100 may be fabricated using gate array technology, such as described in U.S. Patent 4,642,487. The preferred embodiment of the cell comprises the use of CMOS technology where the entire cell of Figure 10 is fabricated on a single silicon substrate as an integrated circuit. (The multiprocessor 100 is sometimes referred to in the singular, even though, as will be described, it is a multiprocessor, specifically four processors.)

The multiprocessor 100 is a stack oriented processor having four sets of registers 101, providing inputs to an arithmetic logic unit (ALU) 102. The ALU 102 comprises two separate ALU's in the presently preferred embodiment.

20

The memory 115 provides storage for a total of 64KB in the currently preferred embodiment, although this particular size is not critical. One portion of the memory is used for storing instructions (ROM code 115a). The next portion of the memory is
5 a random-access memory 115b which comprises a plurality of ordinary static memory cells (dynamic cells can be used). The third portion of the memory comprises an electrically erasable and electrically programmable read-only memory (EEPROM) 115c. In the currently preferred embodiment, the EEPROM 115c employs
10 memory devices having floating gates. These devices require a higher voltage (higher than the normal operating voltage) for programming and erasing. This higher potential is provided from an "on-chip" voltage pump 116. The entire address space for memory 115 addressed through the ALU 102a which is one part of
15 the ALU 102.

The ROM 115a stores the routines used to implement the various layers of the protocol discussed in this application. This ROM also stores routines needed for programming the EPROM 115c. The application program for the cell is stored in ROM 115a
20 and, in general, is a routine which acts as a "state machine" driven by variables in the EEPROM 115c and RAM 115b. RAM 115b stores communications variables and messages, applications

variables and "state machine" descriptors. The cell ID, system ID and communications and application parameters (e.g., group number, member number, announcer/repeater/listener assignments) are stored in the EEPROM 115c. The portion of the

5 EEPROM 115c storing the cell ID is "write-protected" that is, once programmed with the cell ID, it cannot be reprogrammed

The input/output section of the cell comprises four subsections 107, 108, 109 and 110. Three of these subsections 107, 108 and 109 have leads 103, 104, and 105 respectively for

10 communicating with a network and/or controlling and sensing devices connected to the cell. The remaining subsection 110 has a single select pin 106 which can be used to read in commands such as used to determine the cell's ID. As presently

implemented, the subsection 110 is primarily used for timing and

15 counting. The input/output section is addressed by the processor through a dedicated address space, and hence, in effect appears to the processor as memory space. Each I/O subsection can be coupled to each of the subprocessors. This feature, along with the multiprocessor architecture of processor 100, provides for

20 the continuous (non-interrupted) operation of the processor. The I/O section may be fabricated from well-known circuitry; the

presently preferred embodiment is shown in Figures 17 through 23.

The cell of Figure 10 also includes an oscillator 112 and timing generator 111, the latter provides the timing signals particularly needed for the pipelining shown in Figure 13. Operation at a 16mHz rate for the phases 1-4 of Figure 13 is currently preferred, thus providing a 4mHz minor instruction cycle rate. Other well-known lines associated with the cell of Figure 10 are not shown (e.g., power).

All of the cell elements associated with Figure 10 are, in the preferred embodiment, incorporated on a single semiconductor chip, as mentioned.

B. PROCESSOR

The currently preferred embodiment of the processor 100 is shown in Figure 12 and includes a plurality of registers which communicate with two ALU's 102a and 102b. (Other processor architectures may be used such as one having a "register" based system, as well as other ALU and memory arrangements.) The address ALU 102a provides addresses for the memory 115 and for accessing the I/O subsections. The data ALU 102b provides data for the memory and I/O section. The memory output in general is

coupled to the processor registers through registers 146 to DBUS 223.

The 16-bit ABUS 220 provides one input to the address ALU 102a. The base pointer registers 118, effective address registers 119 and the instruction pointer registers 120 are coupled to this bus. (In the lower righthand corner of the symbols used to designate these registers, there is shown an arrow with a designation "x4". This is used to indicate that, for example, the base pointer register is 4 deep, more specifically, the base pointer register comprises 4 16-bit registers, one for each processor. This is also true for the effective address registers and the instruction pointer registers.) The BBUS 221 provides up to a 12 bit input to the ALU 102a or an 8 bit input to the data ALU 102b through register 142. The 4 deep top of stack registers 122, stack pointer registers 123, return pointer registers 124 and instruction registers 125 are coupled to the BBUS.

The CBUS 222 provides the other 8-bit input to the ALU 102 through register 143. The CBUS is coupled to the instruction pointer registers 120, the 4 deep top of stack registers 122, the four carry flags 129, and the 4 deep CRC registers 130 and the 4 deep next registers 131.

The MBUS, coupled to the output of the memory, can receive data from the output of the ALU 102b through register 145b, or from the memory or I/O sections (107-110). This bus through register 146 and the DBUS 223 provides inputs to registers 118,
5 119, 120, 122, 123, 124, 125, 130, 131 and to the carry flags 129.

There is a 16-bit path 132 from the output of the address ALU 102a to the registers 120. The ALU 102b includes circuitry for performing CRC calculations. This circuitry directly connects with the CRC registers 130 over the bidirectional lines 133. The
10 top of stack registers 122 are connected to the next registers 131 over lines 138. These lines allow the contents of register 122 to be moved into registers 131 or the contents of register 131 to be moved into registers 122. As currently implemented, a bidirectional, (simultaneous) swap of data between these
15 registers is not implemented. Four bits of data from the output of the memory may be returned directly either to the instruction pointer registers 120 or the instruction registers 125 through lines 139.

The pipelining (registers 141, 142, 143, 145 and 146) of
20 data and addresses between the registers, ALU, memory and their respective buses is described in conjunction with Figure 13.

The data in any one of the stack pointer registers 123 or any one of the return pointer registers 124 may be directly incremented or decremented through circuit 127.

Both ALU's 102a and 102b can pass either of their inputs to their output terminals, can increment and can add their inputs. ALU 102b in addition to adding, provides subtracting, shifting, sets carry flags 124 (when appropriate), ANDing, ORing, exclusive ORing and ones complement arithmetic. The ALU 102b in a single step also can combine the contents of next registers 131 and CRC registers 130 (through paths 222 and 133) and combine it with the contents of one of the top of stack registers 122 to provide the next number used in the CRC calculations. Additionally, ALU 102b performs standard shifting and provides a special nibble feature allowing the lower or higher four bits to be shifted to a higher or lower four bits, respectively. Also, ALU 102b performs a 3-of-6 encoding or decoding described in Section F.

In the preferred embodiment with a single semiconductor chip for a cell there are basic contact pads on the die for power and ground and all the I/O pins A and B and the "read only" pin 106 (subsections 107, 108, 109 and 110, Figure 12). These contact

pads are used for attachment to package pins for a basic inexpensive package.

In addition to the basic contact pads additional pads in the presently preferred embodiment will be provided with

5 connections to the ADBUS 224 and the MBUS 225 of Figure 12.

One control contact pad may be provided to disable internal memory. By activating the control contact the internal memory is disabled and the data over ADBUS and MBUS is used by the

processors. This allows the use of a memory that is external to
10 the cell. It is assumed that the additional contact pads may not be available for use when the cell is in an inexpensive package.

These additional contacts may be accessed by wafer probe contacts or from pins in packages that have more than the minimum number of pins.

15 The cell as manufactured requires an initialization program.

At wafer probe time the external memory is used for several purpose, one of which is to test the cell. Another use is to provide a program to write the cell ID into the EEPROM during the manufacturing process. Any necessary EEPROM instructions to

20 allow power up boot when the cell is later put in use may be added at this time. Initialization programs and test programs are well-known in the art.

C. PROCESSOR OPERATION

In general, memory fetches occur when the ALU 102a provides a memory address. The memory address is typically a base address or the like on the ABUS from one of the base points in registers 118, effective address registers 119 or instruction pointer register 120 combined with an offset on the BBUS from the stack pointer register 123, return pointer register 124, top of stack registers 122 or the instruction registers 125.

Calculations in the ALU 102b most typically involve one of the top of stack registers 122 (BBUS) and the next registers 131 (CBUS) or data which may be part of an instruction from one of the instruction registers 125.

While in the presently preferred embodiment, the processor operates with the output of the memory being coupled to the DBUS 223 through register 146, the processor could also be implemented with data being coupled directly to the input of ALU 102b. Also, the function performed by some of the other registers, such as the effective address registers 119 can be performed by other registers, although the use of the effective address registers, and for example, the CRC registers, improve the operation of the processor.

In general, for memory addressing, a base pointer is provided by one of the registers 118, 119 or 120 with an offset from one of registers 122, 123, 124 or 125. The address ALU 120a provides these addresses. Also, in general, the ALU 120b
5 operates on the contents of the top of stack and next register; there are exceptions, for example, the instruction register may provide an immediate input to the ALU 102b. Specific addressing and other instructions are described below.

D. MULTIPROCESSOR OPERATION

10 The processor is effectively a multiprocessor (four processors) because of the multiple registers and the pipelining which will be described in conjunction with Figure 13. As mentioned, one advantage to this multiprocessor operation is that interrupts are not needed, particularly for dealing with input and
15 output signals. The multiprocessor operation is achieved without the use of separate ALUs for each processor. In the currently preferred embodiment, economies of layout are obtained by using two ALUs, (102a and 102b) however, only one of the ALUs operates at any given time. (Note the BBUS provides an input to both
20 ALUs.) Therefore, the multiprocessor operation of the present invention may be obtained using a single ALU.

The processing system has four processors sharing an address ALU, a data ALU and memory. A basic minor cycle takes four clock cycles for each processor. The ALUs take one clock cycle and the memory takes one clock cycle. The minor cycles for
5 each processor are offset by one clock cycle so that each processor can access memory and ALUs once each basic minor cycle. Since each processor has its own register set it can run independently at its normal speed. The system thus pipelines four processors in parallel.

10 Each register of Figure 12 is associated with one of four groups of registers and each group facilitates the multiprocessor operation and is associated with a processor (1-4) of Figure 13. Each of the four groups includes one base pointer register, effective address register, instruction pointer register, top of
15 stack register, stack pointer register, return pointer register, instruction register, CRC register, next register, and a carry flag. Each related group of registers corresponds to one of the four processors. Each processor executes instructions in minor cycles, each minor cycle consisting of four clock cycles. During
20 the first clock cycle a processor will gate the appropriate registers onto the ABUS, BBUS and CBUS. In the next clock cycle the ALUs will be active generating data from their inputs of the

ABUS, BBUS and CBUS. Memory or I/O will be active during the third clock cycle, with the address coming from the ALU 102a and data either being sourced by memory or the ALU 102b. The fourth and final clock cycle will gate the results from memory or the

5 ALU 102b into the appropriate register via the DBUS.

A processor can be viewed as a wave of data propagating through the sequence described above. At each step the intermediate results are clocked into a set of pipeline registers. By using these pipeline registers it is possible to separate the

10 individual steps in the sequence and therefore have four steps executing simultaneously. The four processors can operate without interfering with one another even though they share the ALUs, memory, I/O and many control circuits.

The control of a processor including the pipelining is best

15 understood from Figure 11. For each processor there is a 3 bit counter and an instruction register. These are shown in Figure 11 as counters 137a through 137d, each of which is associated with one of the instruction registers 125a through 125d, respectively. Each of the instruction registers is loaded through the DBUS. As

20 an instruction register is loaded, the instruction is coupled to a PLA 212. This PLA determines from the instruction how many minor cycles are required to execute the instruction and a 3 bit

binary number is then loaded into the counter 113a or 113b or 113c or 113d, associated with the instruction register 125a, or 125b, or 125c or 125d being loaded. For instance, for a CALL instruction loaded into instruction register 125c, the binary
5 number 010 (indicating three minor cycles) is loaded into counter 137c. (Up to 8 minor cycles can be used for a given instruction, however, only up to 6 minor cycles are used for any of the instructions in the currently preferred embodiment.) The count value "000" is used to cause a new instruction to be fetched.

10 The count (e.g., 3 bits) in a counter and the instruction (e.g., 12 bits) in its associated instruction register from a 15 bit input to the PLA 136. These 15 bit inputs from each of the respective four sets of count registers and four sets of instruction registers are sequentially coupled to the PLA 136 as will be described. The
15 output of the PLA controls the operation of the processors. More specifically: lines 213 control data flow on the ABUS, BBUS and CBUS; lines 214 control the ALU 102; lines 215 control the memory; (and, as will be described later I/O operation of subsections 107, 108, 109 and 220) and lines 216 control data
20 flow on the DBUS. The specific outputs provided by the PLA 136 for a given instruction is best understood from the instructions set, set forth later in this application. The action taken by the

processors to execute each of the instructions is described with the instruction set.

The outputs from the PLA on lines 213 are coupled directly to the devices controlling data flow on the ABUS, BBUS, and
5 CBUS. The signals controlling the ALU are coupled through a one clock phase delay register 217 before being coupled to the ALU via the lines 214. Since all the registers 217 are clocked at the same rate, the register 217 performs delay functions as will be described. Those signals from the PLA 136 used for memory
10 control are coupled through two stages of delay registers 217 before being coupled to the memory, thus the signals on lines 215 are delayed for two clock phases related to the signals on lines 213. The control signals for the DBUS after leaving the PLA 136 are coupled through 3 sets of delay registers 217 before being
15 coupled to the lines 216 and therefore are delayed three clock phases related to those on lines 213. The registers 217 are clocked at a 6MHz rate, thus when the PLA 136 provides output control signals for a given instruction (e.g., contents of instruction register 125a) the control signals during a first clock
20 phase are coupled to lines 213, during a second clock phase, lines 214; during a third clock phase, 215; and during a fourth clock phase to lines 216. During the first clock phase of each

instruction cycle, the contents of the counter 137a and the instruction register 125a are coupled to the PLA 136. During the second clock phase, the contents of the counter 137b and instruction register 125b are coupled to the PLA 136 and so on
5 for the third and fourth clock phases.

Assume now that instructions have been loaded into the instruction registers 125a through 125d and the counters 137a through 137d have been loaded with the corresponding binary counts for the minor cycles needed to perform each of the
10 instructions. For example, assume that register 125a is loaded with a CALL instruction and that 010 has been loaded into counter 137a. During a first instruction minor cycle, 010 and the 12 bit instruction for CALL are coupled to the PLA 136. From this 15 bit input PLA 136 provides at its output all the control signals
15 needed to complete the first minor cycle of the CALL instruction (e.g., four clock phases) for the ABUS, BBUS CBUS, the ALU, the memory and the DBUS. Since the system uses pipelining multiprocessing, the control signals on lines 213 used to carry out the first clock phase of the CALL instruction which is the
20 inputs to the ALUs.(During this first clock phase the other control lines are controlling the ALU, the memory and the DBUS of other processors, for different instructions in the pipelines.)During

phase 2, the count in counter for 137b and the instruction in register 125b are coupled to the PLA 136. During phase 2, the signals on lines 213 now control the ABUS, BBUS and CBUS inputs to the ALUs for the second processor to carry out the instruction contained in register 125b. During this second clock phase, the signals on lines 214 control the first processor and the ALU to perform the functions needed to carry out the second clock phase of the CALL instruction contained in register 125a. (Note a delay equal to one phase was provided by register 217.) Similarly, during the third phase, the signals on lines 213 control the ABUS, BBUS, and CBUS for the third processor to carry out the instruction contained in register 125c; the signals on lines 214 control the ALU to carry out the instruction contained in register 125b, and the signals on lines 215 control the memory to carry out the instructions in register 125a for the first processor. And, finally, during the fourth clock phase, the instruction from register 125d, along with the count in counter 137d are coupled to the PLA 136. The signals on lines 213 control the ABUS, BBUS and CBUS to carry out the instruction contained within register 125d fourth processor; the signals on lines 214 control the ALU to carry out the instruction in register 125c for the third processor; the signals on lines 215 control the memory to carry

out the instruction in register 125b for the second processor; and the signals on lines 216 control the DBUS to carry out the instruction in register 125a for the first processor.

After four cycles of the 16MHz clock the count in register 137a decrements to 001. Each register is decremented on the clock cycle following the use of the contents of the counters contained by the PLA 136. The input to the PLA 136 thus changes even though the instruction within register 125a is the same. This allows the PLA 136 to provide new output signals needed for the second minor cycle of the CALL instruction. These control signals are rippled through the control through the control lines 213, 214, 215 and 216 as described above. When the count in a counter reaches 000, this is interpreted as an instruction fetch for its associated processor.

Therefore, each of the four processors may simultaneously execute an instruction where each of the instructions has a different number of cycles. The control signals reaching the imaginary line 219 for any given clock cycle represent control signals for four different instructions and for four different processors. For example, the control signals associated with the first processor during a first cycle appear on lines 213; during a second cycle on lines 214; during a third cycle on lines 215; and

during a fourth cycle on lines 216. The control signals needed by the second processor follow behind; those needed by the third and fourth processors following behind those used by the second processor.

5 The pipelining of the signals is illustrated in Figure 13. The multiprocessor operation of the processor 100 of Figure 10 is shown in Figure 13 as four processors, processors 1, 2, 3 and 4. Each one of the groups of registers is associated with one of the processors. The four phases of a single instruction cycle are
10 shown at the top of Figure 13. In Figure 13, registers 101 are used to indicate that the contents from the specific registers called for in an instruction are placed on the ABUS, BBUS and CBUS. The registers are 118, 119 and 120 on the ABUS; 122, 123, 124 and 125 on the BBUS; 120, 122, 129, 130 and 131 on the
15 CBUS.

During a first phase, signals previously stored in the group 1 registers (e.g., two of them) are gated from the registers onto the ABUS, BBUS and CBUS. While this is occurring, signals associated with the group 2 registers are gated from the registers 141, 142,
20 143 into the ALU 102a and 102b. This is shown in Figure 13 as processor 2 under the first phase column. Simultaneous signals are gated from registers 145a and 145b into the memory for

group 3 registers for processor 3. And, finally, during this first phase, signals associated with the group 4 registers are gated from registers 146 onto the DBUS. During the second phase, signals associated with a group 1 registers are coupled from the ALU to registers 145. The data associated with group 2 registers are coupled to memory. The data associated with the group 3 registers is coupled from the register 146 onto the DBUS. Those associated with the group 4 registers are gated onto the ABUS, BBUS and CBUS . And, similarly, during the third and fourth phase of each instruction cycle, this pipelining continues as shown in Figure 13, thus effectively providing four processors.

E. PROCESSOR INSTRUCTIONS

In this section each instruction of the processor is set forth, along with the specific registers and memory operations. Lower case letters are used below to indicate the contents of a register. For example, the contents of the instruction register are shown as "ip". The registers and flags are set forth below with their correlation to Figure 12.

FIGURE 12IDENTIFICATION

5	ip	instruction pointer (14 bits) (fixed range of 0000 - 3FFF) (not accessible to ROM based programs)	120
	ir	instruction register (12 bits) (not accessible to ROM based programs)	125
	bp	base page pointer (14 bits) (fixed range of 8000 -FFFF) (write only)	118
10	ea	effective address pointer (16 bits) (not accessible to ROM based programs)	119
15	sp	data stack pointer (8 bits) (positive offset from bp, grows down)	123
	rp	return stack pointer (8 bits) (positive offset from bp, grows up)	124

	tos	top of data stack (8 bits)	122
	next	item below top of data stack (8 bits)	131
5	crc	used as scratch or in CRC calculations (8 bits)	130
	flags	carry flags; (1 bit) processor ID (2 bits)	129
10			

The top element of the return stack is also addressable as a register, even though it is physically located in RAM.

Instruction Table

15	CALL	1aaa aaaa aaaa	Subroutine call
	CALL lib	0000 aaaa aaaa	Library call
20	BR	0010 1aaa aaaa	Branch
	BRZ	0010 00aa aaaa	Branch on TOS==0

	BRC	0010 11aa aaaa	Branch on Carry set
	CALL interseg	0011 LLLL LLLL	(Subroutine)
5		0000 hhhh hhhh	Two word instructions
	LIT	0101 1ffh bbbb	Constant op TOS
	LDC	0101 111h bbbb	Load Constant
10	ALU	0101 00ef ffff	Top of Stack and NEXT
	RET	0101 0011 1101	Return or Bit set in other instruction
15	IN,OUT	0100 0wrr rrrr	Read/Write I/O Register
	LD,ST bp+a	0100 1waa aaaa	Load, Store
20	LD,ST (bp+p)+a	011p pwaa aaaa	Load, Store
	LDR,STR r	0101 010w rrrr	Load, Store CPU reg

For each instruction, the operation, encoding and timing are set forth below in standard C language notation.

CALL Call Procedure

5

Operation:

 *rp++ = lowbyte (ip);

 *rp++ = hibyte (ip);

10 ip = dest;

Encoding:

intra-segment:

15 1 a a a a a a a a a a a

 dest = ip + a + 1; /* displacement a is always negative */

inter-segment:

 0 0 1 1 L L L L L L L L

20 0 0 0 0 H H H H H H H H

 dest = H:L; /* 16 bit absolute address */

71

library:

0 0 0 0 a a a a a a a a

dest = 0x8000+*(0x8001 + a); /* table lookup call */

5

Timing:

	CALL type	#clocks	specific memory operation
10	intra-seg	3	
		2	*rp++ = lobyte (ip)
		1	*rp++ = hbyte (ip)
		0	ir = *(ip = *dest)
15	interseg	5	
		4	lobyte (ea) = *ip++
		3	hbyte (ea) = *ip
		2	*rp++ = lobyte (ip)
		1	*rp++ = hbyte (ip)
20		0	ir = *(ip = *dest)
	library	4	

72

```

3    *rp++ = lobyte (ip)
2    *rp++ = hbyte (ip)
1    ip = dest
0    ir = *ip

```

5 BR Branch always

Operation:

ip = dest;

10 Encoding:

0 0 1 0 1 a a a a a a a

dest = ip + a + 1; /* displacement a is sign extended */

15

Timing:

#clocks

specific memory operation

20

1

0 ir = *(ip = dest)

73

BRC Branch on carry

Operation:

```

5      if ( CF ) ip = dest;
      else ip++;

```

Encoding:

```

10      0 0 1 0 0 1 a a a a a
      dest = ip + a + 1; /* a is sign extended */

```

Timing:

	#clocks	specific memory operation
15	1	
	0	ir = *(ip = dest)
		or
	0	ir = *(++ip);

BRZ Branch on TOS==0

Operation:

5

```
if (tos==0, tos=next, next= *(++sp) ) ip = dest;
else ++ip;
```

Encoding:

10

0 0 1 0 0 0 a a a a a a

dest = ip + a + 1; /* displacement a is sign extended */

15 Timing:

	#clocks	specific memory operation
20	2	1 tos = next; next = *(++sp);
	0	ir = *(ip = dest)

75

or

0 $ir = *(++ip)$ **LDR** Move register to TOS

5 (includes certain indirect, indexed memory reference)

Operation:

 $*(sp--) = next;$ if (reg) { $next = tos; tos = reg$ } else { $next = bp + TOS$ or $next = (bp + 2p) + TOS$ }

10 Encoding:

0 1 0 1 0 1 0 0 r r r r

reg = r /* see table */

Timing:

		#clocks	specific memory operation
15	(if (bp+p)+TOS)	5	
		4	lbyte(ea) = $*(bp + 2p)$
		3	hbyte(ea) = $*(bp + 2p + 1)$
	(if reg, bp+TOS)	3	
		2	$*sp-- = next$
20			if (reg) $next = tos;$
		1	if (reg) $tos = reg$
			else $next = bp + TOS, ea + TOS$

76

0 ir = *(++ip)

STR Store TOS to register

(includes certain indirect, indexed memory reference)

Operation:

```

5      if (reg) { reg = tos; tos = next; }
      else { bp+TOS = next or (bp+2p)+TOS = next }
      next = *(++sp);

```

Encoding:

0 1 0 1 . 0 1 0 1 r r r r

10 reg = r /* see table */

Timing:

	#clocks	specific memory operation
	(if (bp+p)+TOS) 5	
		4 lobyte(ea) = *(bp+2p)
15		3 hibyte(ea) = *(bp+2p+1)
	if (reg, bp+TOS) 3	
		2 if (reg) reg = tos;
		else bp+TOS,ea+TOS=next
		1 if (reg) tos = next;
20		next = *(++sp);
		0 ir = *(++ip);

Register assignments

	0 0 0 0	Flags	CF x ID1 ID0
5			
	0 0 0 1	CRC low byte	(high byte in TOS)
	0 0 1 0	lowbyte (bp)	/* write */
		next ("OVER" instruction)	/* read */
10	0 0 1 1	highbyte (bp)	/* write */
		tos ("DUP" instruction)	/* read */
	0 1 0 0	sp	
	0 1 0 1	rp	
15			
	0 1 1 0	see RPOP, RPUSH	
	0 1 1 1	*(bp+TOS)	/* indexed fetch,store */
20	1 0 0 0	*(*(bp+0)+TOS)	/* indexed indirect */
	1 0 0 1	*(*(bp+2)+TOS)	/* indexed indirect */

78

1 0 1 0 $*(bp+4)+TOS$ /* indexed indirect */

1 0 1 1 $*(bp+6)+TOS$ /* indexed indirect */

5

RPOP pop return stack

Operation:

10 $*(sp--) = next;$
 $next = tos;$
 $tos = *rp--;$

Encoding:

15

0 1 0 1 0 1 0 0 1 1 1 0

Timing:

20

#clocks

specific memory operation

79

```

2    *sp-- = next
    next = tos;
1    tos = *rp--;;
0    ir = *(++ip)

```

5

RPUSH push tos onto return stack

Operation:

```

10    *(++rp)=tos;
      tos = next;
      next = *(++sp);

```

Encoding:

15

```

0 1 0 1  0 1 0 1  1 1 1 0

```

Timing:

20

#clocks

specific memory operation

80

```

2    *(++rp) = tos;
1    tos = next;
    next = *(++sp);
0    ir = *(++ip)

```

5 IN Move I/O register to TOS

Operation:

```

    *(sp--) = next;
10   next = tos;
    tos = reg;

```

Encoding:

15

```

0 1 0 0 0 0 r r r r r

```

Timing:

20

#clocks

specific memory operation

3

```

2    *sp-- = next

```

81

next = tos;

1 tos = reg ;

0 ir = *(++ip);

5 **OUT** Store TOS to I/O register

Operation:

reg = tos;

tos = next;

10 next = *(++sp);

Encoding:

0 1 0 0 0 1 r r r r r

15

Timing:

#clocks

specific memory operation

20

3

2 reg = tos;

1 tos = next;

82

next = *(++sp);

0 ir = *(++ip);

LDC load constant (into TOS)

5

Operation:

*sp-- = next;

next = tos;

10 tos = constant;

Encoding:

0 1 0 1 1 1 1 H b b b b

15 if (H==0) constant = 0000:bbbb;

else constant = bbbb:0000

Timing:

#clocks

specific memory operation

20

3

2 *(sp--) = next;

next = tos;

83

1 tos = constant;
0 ir = *(++ip)

LD (bp+a) load from base page

5

Operation:

*sp-- = next

next = tos

10 tos = *(bp+source);

Encoding:

0 1 0 0 1 0 a a a a a a

15

source = aa aaaa

Timing:

#clocks

specific memory operation

3

20

2 *sp-- = next;
 next = tos;

84

```

1    tos = *(bp+source);
      0    ir = *(++ip);

```

```

LD (bp+p)+a    load indirect
5              ( TOS with byte addressed by pointer at bp+offset
                then indexed by TOS)

```

Operation:

```

10    *sp-- = next;
      next = tos
      tos = *(* (bp+2p)+offset);

```

Encoding:

```

15    0 1 1 p p 0 a a a a a a
      offset = aa aaaa

```

Timing:

	#clocks	specific memory operation
20	5	
	4	lobyte(ea) = *(bp+2p)
	3	hibyte(ea) = *(bp+2p+1)

85

```

2    *sp-- = next;
    next = tos;
1    tos = *(ea+offset)
0    ir = *(++ip)

```

5

ST (bp+a) store into base page

Operation:

```

10    *(bp+dest) = tos
    tos = next;
    next = *(++sp)
    Encoding:

```

```

15    0 1 0 0 1 1 a a a a a a
    dest = aa aaaa

```

Timing:

	#clocks	specific memory operation
20	3	
	2	*(bp+dest) = tos;

86

```

1   tos = next;
    next = *(++sp);
0   ir = *(++ip)

```

5 ST (bp+p)+a store indirect
 (TOS into byte addressed by pointer at bp+2p offset by a)

Operation: =

```

10  *(*(bp+2p)+offset)=tos;
    tos = next;
    next = *(++sp)

```

Encoding:

15

```

0 1 1 p p 1 a a a a a a
offset = aa aaaa

```

Timing:

20

#clocks specific memory operation

5

```
5
4    lobyte(ea) = *(bp+2p)
3    hibyte(ea) = *(bp+2p+1)
2    *(ea+off)=tos
1    tos = next;
    next = *(++sp)
0    ir = *(++ip)
```

[ALU Group]

10 Operation:

```
    if (r==1) {
        hibyte(ip) = *rp--;
        lobyte(ip) = *rp--;
15    }
    pipe = tos;          /* internal processor pipeline */
    tos = tos op next;
    switch (s) {
        case 0: next = next;          /* typical unary op */
20        case 1: next = *(++sp);      /* typical binary op */
    }
```

Encoding:

0 1 0 1 0 0 r f f f f

op = ffff /* s equal to high order f bit */

s = (1==unary op), (0==binary op)

5

Op Table:

	code	operation	carry state
10	00000	tos + next	arith carry
	00001	tos + next + carry	arith carry
	00010	next - tos	arith borrow
	00011	next - tos - carry	arith borrow
	00100	tos - next	arith borrow
15	00101		
	00110		
	00111		
	01000	tos AND next	unchanged

	01001	tos OR next	unchanged
	01010	tos XOR next	unchanged
	01011		
	01100	drop	unchanged 01101
5	swap-drop	unchanged	
	01110		
	01111	CRC step	unchanged
	10000	asl (TOS)	tos7
	10001	asr (TOS)	0
10	10010	rotate left(tos)	tos7
	10011	rotate right (tos)	tos0
	10100	tos	parity(TOS)
	10101		
	10110		
15	10111	3of6 encode	set if not valid

	11000	lsl (TOS)
	11001	lsr (TOS)
	11010	shift left by 4
	11011	shift left by 4
5	11100	swap
	11101	tos (NOP)
	11110	NOT(TOS)
	11111	3of6 decode

Timing:

10

	s	#clocks	specific memory operation
	1	2 (4)	
		(if r==1)	3 hibyte(ip) = *rp--;)
15		(if r==1)	2 lobyte(ip) = *rp--;)
			1 tos = alu output
			0 ir = *(++ip)
	0	3 (5)	
		(if r==1)	4 hibyte(ip) = *rp--;)
20		(if r==1)	3 lobyte(ip) = *rp--;)
			2 tos = alu output

91

1 *(++sp) = next

0 ir = *(++ip)

SWAP special case

5

The exchange of TOS with NEXT is a special case of the ALU ops using the direct data path between TOS and NEXT. The NEXT register receives a cc of the TOS via a pipeline register, prior to TOS being loaded with the conter of NEXT (non-simultaneous transfer).

10

NOP

Operation:

15 ++ip;

Encoding:

short	0 0 1 0 1 0 0 0 0 0 0 0
-------	---------------------------

20

long	0 1 0 1 0 0 0 1 1 1 0 1
------	---------------------------

92

Timing:

		#clocks	specific memory operation
5	short	1	
	(BR +1)		0 ir = *(++ip)
	long	2	
			1 tos = tos
			0 ir = *(++ip)
10	RET	return from subroutine	

Operation:

```

    hbyte(ip) = *rp--
15    lbyte(ip) = *rp--
    ++ip;

```

Encoding:

```

20      0 1 0 1 0 0 1 1 1 1 0 1

```

Timing:

	#clocks	specific memory operation
-	4	
5	3	hibyte(ip) = *rp--
	2	lobyte(ip) = *rp--
	1	tos = tos
	0	ir = *(++ip)

[LITERAL Group]

10

Operation:

tos = tos op constant;

Encoding:

15

0 1 0 1 1 f f H c c c c

op = ff

if (H==0) constant = 0000:cccc

else constant = cccc:0000

Op Table:

20

code

operation

carry state

00	tos + constant	arith carry
01	tos - constant	arith borrow
00	tos AND constant	
11	constant (see LDC)	

5

Timing:

	#clocks	specific memory operation
	2	
	1	tos = alu output
10	0	ir = *(++ip)

F. THREE-OF-SIX CIRCUITRY

As previously mentioned, the ALU 102b contains means for encoding four bit nibbles into six bit words for transmission (encoder of Figure 14) and for decoding six bit words into the four bit nibbles (decoder of Figure 15). Both the encoder and decoder use hardwired logic permitting the conversion to be performed very quickly in both directions. Moreover, there is a circuit shown in Figure 16 to verify that each six bit word received by the cell is in fact a three-of-six code, that is, three zeroes and three ones (Figure 9).

Referring to Figure 14 the register 142 is illustrated with four bits of the register containing data D0 through D3. If the ALU is commanded to encode this data, the resultant six bits will be coupled into the latch register 145b. To obtain the conversion shown in Figure 9, the D0 bit is directly coupled into first stage of register 145b and becomes E0, the encoded bit. Also, the bit D3 is directly coupled into the register and becomes E5. Each of the remaining bits E1 through E4 are provided by the logic circuits 153 through 150, respectively. Each of these logic circuits are coupled to receive D0, D1, D2 and D3. Each logic circuit contains ordinary gates which implement the equation shown within its respective block. These equations are shown in standard "C" language ("&" = logical AND, "!" = logical NOT, and "|" = logical OR.) These equations can be implemented with ordinary gates.

The decoder of Figure 15 is shown in a similar format. This time the six bits of the encoded data are shown in register 142. The decoded four bits of data are shown in the register 145. To implement the pattern assignment shown in Figure 9, the E0 bit is coupled directly to the register 145 and becomes D0. The E5 bit is coupled directly to the register 145 and becomes the D3 bit. Logic circuits 154 and 155 provide the bits D2 and D1, respectively. Circuit 154 is coupled to receive the bits E0, E3, E4

and E₅ while the circuit 155 receives E₀, E₁, E₃, and E₅ (E₂ is not used to provide the D₀ through D₃ bits.) (Some of the six bit patterns are not used and others are used for synchronization and thus do not require conversion into a data nibble.) The circuits
5 154 and 155 are constructed from ordinary logic gates and implement the equations shown. The symbol " ^ " represents the exclusive OR function in the equations.

The circuit of Figure 16, as mentioned, verifies that the received six bit words do contain three zeroes and three ones.
10 The encoded words are shown coupled from the top of stack register 122 into the two full adders, 157 and 158. These adder stages are contained within the ALU 102b. Each adder receives an X, Y and carry input and provides a sum and carry output. These ordinary adder stages are each coupled to receive one bit of the
15 encoded word as shown. (Any coupling of each bit to any input of address 157 and 158 may be used.) The carry outputs of the adders 157 and 158 are coupled to the exclusive OR gate 159; the sum outputs of the adders 157 and 158 are coupled to the
20 exclusive OR gate 160. The output of the gates 159 and 160 are coupled to the input terminals of an AND gate 161. If the output of this AND gate is in its high state the word in the register 102 contains three ones and three zeroes. Otherwise, the output of

the gate 161 is in its low state (abort condition). The incoming packets are checked to determine that each six bit word is valid, while it is decoded into the four bit nibbles.

IV. INPUT/OUTPUT SECTION

5

A. General

The I/O section includes a plurality of circuit elements such as a ramp generator, counter, comparator, etc., which are interconnected in different configurations under software control. Examples of this are shown below for the analog-to-digital (A to D) and digital-to-analog (D to A) operations. These elements with their software configurable interconnections provide great flexibility for the cell, allowing it to perform many tasks. The entire I/O section is preferably fabricated on the same "chip" which includes the processor.

15

B. Buffer Section

As shown in Figure 10 and previously discussed, each of the cells includes four input/output I/O subsections; three of the subsections 107, 108, and 109 each have a pair of leads, identified as Pin A and Pin B. The fourth subsection 110 has a single "read only" pin 106. Any of the four subsections can communicate with any of the four subprocessors. As shown in

20

Figure 12, this is easily implemented by connecting the address bus (ADBUS) and the memory bus (MBUS) to each of the four I/O subsections. Use of the MBUS through the register 146 to the DBUS allows the I/O subsections to communicate with the
5 processor registers.

Each Pin A and Pin B can receive and provide TTL level signals and is tristated. In the currently preferred embodiment, each pin can sink and source approximately 40milliamps (except for pin 106). All the Pin A's can be programmed to provide an
10 analog output signal and a digital-to-analog converter is included in three of the I/O subsections 107, 108 and 109 to provide an analog output on Pin B. An analog input signal on any of the Pin B's can be converted to a digital count since three of the I/O subsections include A to D converters coupled to these pins. Each
15 pin pair (Pin A and Pin B) can operate as a differential amplifier for input signals, a differential receiver, and a differential transmitter and a differential voltage comparator. The I/O subsections can be used to perform many different functions, from simple switching to, by way of example, having two pin
20 pairs coupled to drive the windings of a stepping motor.

The circuits shown in Figures 17-23 are repeated in subsections 107, 108 and 109. Those circuits associated with

Pin A and Pin B (such as the buffer sections of Figure 17) are not fully contained in the I/O subsection 110. Only sufficient buffering to allow data to be read on Pin 106 is needed.

Referring to the I/O buffer section of Figure 17, outgoing
5 data is coupled to Pin A through the buffer 163. Similarly,
outgoing data is coupled to Pin B through the buffer 164 after the
data passes through the I/O control switch 165. This outgoing
data, by way of example, is coupled to Pin A from the register
206 of Figure 23 through gate 208 of Figure 19. The control
10 switch 165 is used to enable outputs to Pin A through the buffer
163, when enable A (EN.A) is high (line 166). Moreover, the
switch enables the output to Pin B when enable B (EN.B) is high
(line 167) and enables outputs to both pins (with the output to Pin
B being inverted) when enable RS-485 is high (line 168). The
15 outgoing analog signal to Pin A is provided through the switch
175 when the enable analog output signal is high.

Incoming signals to Pin A are coupled to one input terminal
of the differential amplifier 169. The other terminal of this
signal receives a reference potential (e.g., 2.5 volts). This
20 amplifier also includes the commonly used hysteresis mode to
prevent detection of noise. This mode is activated when the
enable hysteresis (Pin A) signal coupled to amplifier 169 is high.

The output of amplifier 169 is coupled to a transition detection circuit 171 which simply detects each transition, that is, a zero to one, or one to zero.

The inputs to Pin B are coupled to one terminal of a differential amplifier 170 which may be identical to amplifier 169. The amplifier 170 receives the enable hysteresis (Pin B) signal. The other input to amplifier 170 (line 176) can be coupled to receive one of several signals. It can receive a DC signal used for voltage comparisons, a ramp which shall be discussed later, the signal on Pin A for differential sensing, or a reference potential (e.g., 2.5 volts). The output of the amplifier 170 can be inverted through the exclusive OR gate 177 for some modes of operation. A transition detector 172 is associated with the Pin B inputs, again to detect transitions of zero to one or one to zero.

15 C. I/O Counting/Timing

Each of the cells includes a timing generator (RC oscillator) for providing a 16MHz signal. This signal is connected to a rate multiplier 178 contained in the I/O section (Figure 18). The multiplier 178 provides output frequencies to each I/O subsection. This multiplier provides a frequency f_0 equal to:

$$f_0 = \frac{16\text{MHz}}{2^{16}} \times (\text{LOADED VALUE})$$

The loaded value is a 16 bit word loaded into a register of a rate multiplier 178. The rate multiplier comprises four 16-bit registers and a 16-bit counter chain. Four logic circuits allow selection of four different output signals, one for each subsection. Two bus cycles (8 bits each) are used to load the 16 bit words into the register of the rate multiplier 178. As can be seen from the above equation, a relatively wide range of output frequencies can be generated. These frequencies are used for many different functions as will be described including bit synchronization.

The output of the multiplier 178 in each of the subsection is coupled to an 8 bit counter 179. The counter can be initially loaded from a counter load register 180 from the data bus of the processors. This register can, for example, receive data from a program. The count in the counter is coupled to a register 181 and to a comparator 182. The comparator 182 also senses the 8 bits in a register 183. The contents of this register are also loaded from the data bus of the processors. When a match between the contents in the counter and the contents of register 183 is detected by comparator 182; the comparator provides an event signal to the state machine of Figure 19 (input to multiplexers 190 and 191). The contents of the counter 179 can

be latched into register 181 upon receipt of a signal from the state machine (output of the execution register 198 of Figure 19). The same execution register 198 can cause the counter 179 to be loaded from register 180. When the counter reaches a full count
5 (terminal count) a signal is coupled to the state machine of Figure 19 (input to multiplexers 190 and 191).

D. I/O CONTROL AND STATE MACHINE

Referring to Figure 19, the processor MBUS communicates
10 with registers 185 and 186 both of which perform masking functions. Three bits of the register 185 control the selection of one of the five lines coupled to the multiplexer 190; similarly, 3 bits of the register 186 control the selection of one of the five lines coupled to the input of the multiplexer 191. The output of
15 the masking registers 185 and 186 are coupled to a multiplexer 187. The five bits from the multiplexer 187 are coupled to a register 198. Each of these bits define a different function which is, in effect, executed by the state machine. Specifically, the bits control load counter, latch count, enable ramp switch, pulse
20 Pin A., and pulse Pin B.

The multiplexers 190 and 191 both receive the terminal count signal from counter 179 of Figure 18, the compare signal

from comparator 182, the ramp start signal from the ramp generator 200 of Figure 20, and the transition A and B signals from the transition detectors 171 and 172, respectively of Figure 17. The one bit output from each of the multiplexers 190 and 191 is coupled to an OR gate 188. This OR gate is biased in that if an output occurs simultaneously from both multiplexers 190 and 191, priority is given to multiplexer 190. The output of the multiplexer 190 controls the multiplexer 187 with the signal identified as "which event". This signal is also stored in the 3x3 first-in, first-out (FIFO) buffer 199. This signal indicates which MUX 190 or 191 has received an event and this data is stored along with the inputs to Pin A and Pin B (Figure 17) in the FIFO 199.

The state machine for each of the I/O subsections comprises 4 D-type flip-flops connected in series as shown in Figure 19 within the dotted line 189. The flip-flops 194 and 196 receive the 8mHz signal whereas the flip-flops 193 and 195 receive the complement of this timing signal. The clocking signal (CLK) is obtained from the Q output of the flip-flop 194 and is coupled to register 198 and FIFO 199. The clear signal received from the Q terminal of flip-flop 196 is coupled to the register 198.

In operation, the masking registers 185 and 186 are loaded under software control. The bits from register 185, for instance, cause the selection of one of the input lines to multiplexer 190, for example, terminal count. Then the circuit of Figure 19 waits
5 for the signal terminal count. When the signal terminal count occurs the state machine begins operating and the five bits of data from register 185 are connected through multiplexer 187 into register 198. The state machine causes an output to occur on one of the lines from register 198 causing, for example, a pulse
10 to be generated on pin A. Similarly, a word in register 186 can be used to cause, again by way of example, the counter to be loaded.

The flip-flops 203 and 204 are clocked by the output of register 198. These flip-flops allow the output signal to be controlled. The OR gate 208 permits data from a shift register
15 206 of Figure 23 to be coupled to Pin A. This register is discussed later.

The low order 6 bits of the ADBUS are input to decoders in the I/O subsections 107, 108, 109 and 110 of Figure 12. Two of the bits are used to select a specific I/O element and the rest are
20 decoded to control an operation. The PLA 136 of Figure 11 has generalized outputs 215 connected in parallel to all I/O subsections 107, 108, 109 and 110 to select the ABUS clock cycle

for data to be used for controlling operation of the I/O subsections.

E. ANALOG TO DIGITAL AND DIGITAL TO ANALOG CONVERSION

- 5 Referring first to Figure 20, the I/O subsystem includes a ramp generator 200 which continually generates ramps of a known period. The output of the ramp generator is buffered through buffer 201 and selected by switch 202. The switch, as will be described, is selected at some count (time) following the
- 10 start of each ramp, thereby coupling the same potential to the capacitor 203. This capacitor becomes charged and potential is coupled through buffer 204 to Pin A when the switch 175 is closed. (Switch 175 is shown in Figure 17.) The switch 202, capacitor 203, and buffer 204 act as a sample and hold means.
- 15 In Figure 21 several of the circuit elements previously described have been redrawn to describe how a digital to analog conversion occurs and to show how the circuit elements of the I/O subsection can be reconfigured through software by the I/O control and state machine of Figure 19 to perform different
- 20 functions.

For a digital to analog conversion an appropriate frequency (f_0) is selected from the rate multiplier 178 or counter 179 of

Figure 18, which corresponds to the period of the ramps being generated by ramp generator 200 (Figure 21). A digital value which corresponds to the desired output analog signal is loaded into the register 183. When a ramp begins the ramp start signal is coupled through the state machine 189 of Figure 19 (for example, through the multiplexer 190) and the flip-flops). This causes the counter 179 to be cleared (e.g., all zeroes). The f_0 signal then counts into counter 179. The comparator 182 then compares the contents of the counter 179 with the contents of register 183. When the two words are the same, the compare signal is applied through multiplexer 191 again causing the state machine to be activated as indicated by "SM₁", 189 and the switch 202 of the sample and hold means to close. For each ramp generated by the ramp generator, the ramp switch 202 is closed (e.g., for 500 nanoseconds) causing the capacitor 203 to be charged to a DC voltage which corresponds to the digital number placed in register 183.

One manner in which the A-D conversion can be performed is shown in Figure 22. The input analog signal is applied to one input terminal of the differential amplifier 170. The ramp is applied to the other terminal of the amplifier 170. Initially, when the ramp is started, the state machine 189 causes the

counter 179 to be loaded from register 180 (e.g., all zeroes). The counter is clocked at a frequency (f_0) suitable to the period of the ramps. When the transition detection 172 detects that the potential on Pin B and the ramp have the same potential, the state machine 189 causes the count in the counter 179 to be latched into latch 181. The digital word in latch 181 corresponds to the DC potential on Pin B, thereby providing the analog to digital conversion.

F I/O COMMUNICATIONS

As previously discussed, for instance, in conjunction with Figure 1, each cell can transmit data over communications lines or other links. The cells in a subchannel transmit data at the same rate typically determined by the communications link being employed, for example, 10K BPS in a noisy environment such as for power lines. In the currently preferred embodiment, the cells do not have crystal oscillators but rather rely upon RC oscillators. The latter are not particularly stable and frequency variations occur both with temperature and as a result of processing variations. Moreover, there is no synchronization provided between cells, thus, each cell must provide synchronization to the incoming data in order to properly read the data. One feature of all cells is that they detect and store the

frequency of the incoming data and when acknowledging a packet they can transmit at the frequency that the original packet was transmitted. This reduces the burden on cells to synchronize when they are receiving an acknowledgement packet.

5 Referring to Figure 23 during the hunt mode, an I/O subsection is hunting for data. During this mode, the rate multiplier provides a frequency (f_0) to the counter 179 and a number is loaded into register 183 from the MBUS. Matches occur and are detected by comparator 182 at a frequency corresponding
10 to the expected incoming data rate. Specifically, the terminal count of counter 179 is synchronized to the transitions. As indicated by the dotted line 201, the processor continually searches for transitions from the transition detectors 171 and 172 of Figure 17. When transitions occur, the processor
15 determines whether the transitions occurred before or after the terminal count and then adjusts the frequency (f_0) until the terminal count occurs at the same time that the transitions are detected. This frequency is the shifting rate for the shift register 206. (The steps performed by the processor are shown in
20 Figure 23 as blocks 210 and 211.) The number loaded into register 183 provides a phase shift between the time at which transitions occur and the ideal time to shift data in the register

206. This prevents the shifting of data during transitions. Note counter 179 is reloaded (e.g., all zeroes) each time it reaches a terminal count.

When bit synchronization occurs, rate needed for the
5 synchronization (16 bit word) is stored within the processor memory and used to set the transmit frequency when acknowledging the packet for which the rate was developed. This stored bit rate as discussed later is used in the contention back-off algorithm allowing slot periods (M) to be matched to the last
10 received bit rate.

The comparator output is used as a shift rate for a six bit shift register 206. During the hunt mode, the data from Pin B is continually shifted through register 206. The preamble to a packet as shown in Figure 9 (010101-bit synch) is shifted along
15 the shift register 206 and the shifting rate adjusted so that synchronization/lock occurs. When the packet beginning flag appears (nibble synch-101010) the last two stages of the register 206 will contain ones and this will be detected by the AND gate 207. A binary one at the output of gate 207 ends the
20 hunt mode and provides the nibble synchronization. When this occurs, the data is clocked out of the shift register (6 bits) into a data latch 235 and from there the data can be clocked into the

processor and converted into 4 bit nibbles. Another circuit means is present to detect all zeroes in the shift register 206. When this occurs, the processor and shift register return to the hunt mode. The number loaded into register 183 provides a phase shift
5 between the time at which transitions occur and the ideal time to shift data in and out of the register 206. This prevents the shifting of data during transitions.

Data which is to be transmitted is transferred into the data register 205. (Note only 6 bits representing a four bit nibble are
10 transferred into the data register 205.) These 6 bits are then transferred into the shift register 206 and shifted out at the shift rate. As mentioned, if the packet being shifted out represents an acknowledgement, the shift rate corresponds to the rate of the incoming data. If the outgoing packet on the other
15 hand is being sent to several cells, the shift rate is the nominal shift rate for the transmitting cell.

(Note that in Figure 23, data is shown leaving the register to only Pin A. For differential modes, the complement of Pin A is driven onto Pin B - and other variations are possible.)

G. I/O REGISTERS AND RESOURCE SHARING

Each I/O subsection has a number of registers which have bidirectional connections to the MBUS. These registers are in the I/O subsections 107, 108, 109 and 110 of Figure 12. The reading and writing of these registers under processor program control configures the I/O subsystems for proper operation. Figure 12 illustrates the four I/O subsections 107, 108, 109 and 110 and shows the connections to the low eight bits of the MBUS and the low six bits of ADBUS. Two ADBUS bits select one of the four I/O units and the remaining four bits are decoded to select one of the I/O control and status registers (described below) of that subsection. There are two lines from the PLA 136 of Figure 11 to control the action of the I/O subsections. One line is "Read" and the other line is "Write". When appropriate these lines are active on phase 3 of the clock cycles.

The I/O registers, functions and bit definitions are described below:

WRITE REGISTERS: (Controlled by the "Write" line).

- 20 Event 0 Configuration Register: register, masking, 185 Figure 19:
- Bit 0: Upon event Toggle pin A
 - Bit 1: Upon event Toggle pin B
 - Bit 2: Upon event Latch 8 bit count
 - Bit 3: Upon event close Ramp switch (momentary on)

Bit 4: Upon event Load 8 bit counter

Bits5-7: Input Multiplexer: MUX 190, Figure 19.

- 000 Transition on pin A
- 001 Transition on pin B
- 5 010 Terminal Count event
- 011 Count Compare event
- 100 Ramp start event
- 101 Pin B compare event

10 Event 1 Configuration Register: masking register 186, Figure 19;

- Bit 0: Upon event Toggle pin A
- Bit 1: Upon event Toggle pin B
- Bit 2: Upon event Latch 8 bit count
- Bit 3: Upon event close Ramp switch (momentary on)
- 15 Bit 4: Upon event Load 8 bit counter

Bits5-7: Input Multiplexer: MUX 191, Figure 19

- 000 Transition on pin A
- 001 Transition on pin B
- 010 Terminal Count event
- 20 011 Count Compare event
- 100 Ramp start event
- 101 Pin B compare event

I/O REGISTERS AND RESOURCE SHARING

25

8 Bit Counter Load Register: Counter load register 180;
Figure 18

Bits 0-7 = count

30 Write Communications Data Out Register: data register 205,
Figure 23;

Bits 0-7 - data

Write Communications Configuration Register: (not shown)
35 (loaded from MBUS)

Used to configure the communications subsystem for

113

transmit and receive functions.

Bit 0: 0 = Receive, 1 = Transmit

Bit 1: NOP

Bit 2: NOP

5 Bit 3: Shift Register enable

Bit 4: Enter Hunt Mode

Bit 5: NOP

Bit 6: NOP

Bit 7: NOP

10

Output Configuration Register 0: (not shown) (loaded from MBUS)

Used for setting analog and digital pin configurations.

Bit 0: Enable pin A analog out

Bit 1: Enable pin A digital out

15 Bit 2: Enable pin A pullup

Bit 3: Enable pin A pulldown

Bit 4: Enable pin B inversion

Bit 5: Enable pin B digital out

Bit 6: Enable pin B pullup

20 Bit 7: Enable pin B pulldown

Output Configuration Register 1: (now shown) (loaded from MBUS)

Used for enable and compare functions.

Bit 0: Enable 8 bit counter

25 Bit 1: Compare pin B to TTL reference

Bit 2: Compare pin B to adjustable D.C reference

Bit 3: Compare pin B to Ramp voltage

Bit 4: Compare pin B to pin A

Bit 5: Enable RS-485 driver

30 Bit 6: Enable input hysteresis on pin A

Bit 7: Enable input hysteresis on pin B

Output Configuration Register 2: (not shown) (loaded from MBUS)

Used for setting pin logic levels.

35 Bit 0: Execute, load 8 bit counter with value in 8 bit
Counter Load Register

Bit 1: Set pin A to logic level 1
Bit 2: Set pin A to logic level 0
Bit 3: Set pin B to logic level 1
Bit 4: Set pin B to logic level 0

5

Lower Half of Rate Multiplier Register: rate multiplier 178,
Figure 18
Lower byte of rate multiplier

10

Upper Half of Rate Multiplier Register: rate multiplier 178,
Figure 18

8 Bit Compare Load Register: compare load register 183,
Figure 18
Byte for comparison

15

READ REGISTERS: (controlled by "Read" line);

Read Event FIFO: FIFO 199, Figure 19

Bit 0: 0=Event 1 occurred
1=Event 0 occurred
Bit 1: Pin A level during occurrence of event
Bit 2: Pin B level during occurrence of event

20

Read I/O Condition Register:

I/O Status:
Bit 0: Input pin A
Bit 1: Input pin B
Bit 2: 1=ramp compare
Bit 3: NOP
Bit 4: NOP
Bit 5: 1=FIFO has data
0-FIFO empty

25

30

8 Bit Counter Latch: register 181, Figure 18
Count Byte

35

Communications Data Register: data latch 235, Figure 23
Data Byte

Communications Status Register: (not shown) (reads onto MBUS)
5 Bit 0: Receive mode: 1=data available in shift register
Transmit mode: 0=transmit latch ready
Bit 1: 1=in Hunt Mode from Figure 23

RESOURCE SHARING:

In the presently preferred embodiment there are five resources shared among the processors. They are the EEPROM and the four I/O subsections. A hardware "Semaphore Register" (SR) and five words in RAM are used in controlling resource sharing. Figure 30 illustrates how the multiprocessors share common resources. The SR 95 of Figure 12 reads and writes to bit 0 of the MBUS.

Each RAM word will contain one state: Idle, Proc.#1, Proc.#2, Proc. #3 or Proc. #4. A processor may interrogate a RAM location before assignment of resource to see if a resource is busy. If the resource is not assigned it will then access the Semaphore Register as described below. (Alternately, a processor may, skip the initial RAM interrogation step and check the RAM location after it has accessed the Semaphore Register). If the resource already busy the processor must clear the Semaphore Register to "0" and wait to try again. If the resource is "Idle" the processor assigns a resource by changing the state of the RAM Register from "Idle" to "Proc:#x" and then clearing the Semaphore Register to "0". When the processor is finished with the resource, clears the RAM location to "Idle".

The SR is a one bit hardware register. During phase 3 of its respective cycle, if required, each processor may access the SR. In time sequence, this means that the processors may access the SR 295

once on one of four successive clock cycles (e.g., phases). The SR 295 is normally set to "0". In Figure 30, processors #1 and #3 are not requesting use of the SR 295. Processor #2 is shown accessing the SR. If it receives a "0" at the beginning of the cycle it knows nothing is being currently assigned or cleared and it sets the appropriate RAM location and if it contains "Idle" the processor inserts its "Proc. #" thus assigning the resource and then "clears" the SR to "0". If the processor found that another processor was using the shared resource it does not assign its Proc. # and it then "clears" the SR to "0". In this event it must wait and try again.

Some operations such as those on the EEPROM may take many clock cycles so the processor should "assign" the RAM register but release the SR 295 while it is using the shared resource. When the processor is through with its operation using the assigned RAM location it accesses the SR again until it finds a "0". It then "clears" the RAM location to "idle" and "clears" the SR 295 to "0". Whenever a processor accesses the SR 295 and finds a "1" it leaves the SR 295 in the "1" state and must wait to try again.

In the example in Figure 30 Processor #4 is shown as needing a shared resource. It interrogates the SR to find out if it is free. The processor uses a "test&set" operation and since the SR 295 was already "1" the test & set operation leaves the register with a "1". It

must now wait and try again. It will keep trying until it gets access to the SR 295 and it finds the resource in the RAM word is "idle".

V. PROTOCOL

5

A. CONTENTION IN GENERAL

In a typical application the communications network among the cells is lightly loaded and the cells will experience little or no contention delay. In the case of heavy traffic, the network can
10 saturate. A heavy load will generate collisions and hence require retransmissions. If retransmissions continue to collide, the network can possibly saturate. The contention backoff algorithm used in the network quickly spreads the traffic over a longer time period so that the system can recover from saturation. If the
15 traffic is not spread over a long time period, the system will be unstable; it will not recover from saturation.

Access to a subchannel under contention conditions is regulated by two mechanisms, deferring and backing off. Deferring is a collision avoidance technique used in group
20 acknowledgements. Backing off is a traffic or load leveling technique.

Deferring consists of counting free slots. When the number of free slots that the cell has seen equals the defer count, the cell transmits its packet in the next available slot.

When backing off, the cell increases its waiting time before
5 attempting to retransmit a packet that has suffered a collision. The amount of this increase is a function of the number of collisions or retransmissions. The algorithm implementing this function is called the backoff or contention algorithm.

The network uses a carrier sense multiple access method of
10 resolving contention for the communications channel. When a cell is ready to transmit it first listens to the communications channel. If it hears another cell transmitting, it waits for a clear channel. Once it detects a clear channel, a cell may delay before transmitting. The method of determining that delay is
15 determined by the contention algorithm.

Time on the channel is measured in slots, each slot being M bits at the most recently detected receive baud rate (i.e., shift rate). When a cell delays before transmitting, it waits an integral number of slots. When a cell detects a clear channel, it
20 may delay and then when it is ready to transmit, it attempts to transmit on a slot boundary. If a cell is transmitting a packet that has suffered a collision, it delays a time period determined

by the backoff algorithm. Backoff delay is randomized uniformly over N slots, N is adjusted by the backoff algorithm. Its smallest value is 2 and it is adjusted upward by the backoff algorithm before each retransmission of a packet. Its maximum value is

5 2^{10} .

B. GROUP ACKNOWLEDGEMENT PACKET CONTENTION

A packet from a group announcer to a set of group listeners will cause each of those listeners to send an acknowledgement to the announcer. Without a method of arbitrating contention among those acknowledgements, they will always collide. To avoid this problem, a built in reservation system for group acknowledgements is used. A listener cell uses its group member number to determine which slot to use for its acknowledgement.

10 Group member 5 will transmit its acknowledgement in the 5th free slot following reception of the original packet. The result is that group member 1 will transmit its acknowledgement in the first slot following the original packet. Group member two will transmit its acknowledgement in the first slot following first

15 group member's acknowledgement. This process continues until

20 the last group member has replied to the original packet. If a

group member does not reply and thus leaves its reply slot empty, the next group member replies in the next slot.

The contention and I/O state diagram is shown in Figure 24. The following table sets forth the states and their descriptions.

5	Contention States		
10	State	Name	Description
	0	Idle	Time the slot boundaries while looking for receive data transitions.
	1	Bit Sync	Establish baud rate synchronization with received signal.
	2	Byte Sync	Wait for the start of packet flag.
15		3	Rcv
			Receive the packet.
	4	IPG Delay	Inter Packet Gap Delay. Delay for n bit times after the end of the last packet on the subchannel (whether this neuron transmitted it or received it).
20		5.	Backoff Delay Wait M slots where M was set by the last execution of the backoff algorithm or by the ARQ protocol software.
25	6.	Xmt	Transmit a packet in the next slot.
	7.	Jam	Transmit a jam pattern (all ones) for the jam period (specified in bit times). Execute the backoff algorithm to set the backoff slot count.
30			

Contention State Transitions

	State	Event	Action	Next State
5	0. Idle	A. Transitions Detected	none	1. Bit Sync
	0. Idle	L. Packet to Xmt	none	5. Backoff Delay
	1. Bit Sync	B. Sync Achieved	none	2. Byte Sync
10	1. Bit Sync	G. No Transitions Byte Sync	none	4. IPG Delay
	2. Byte Sync	F. Hunt Timeout	none	1. Bit Sync
	2. Byte Sync	C. Starting Flag Detected	none	3. Rcv
15	3. Rcv	E. Abort Detected	none	1. Bit Sync
	3. Rcv	D. Ending Flag	Set Pckt Rcvd Flag	4. IPG Delay
	3. Rcv	N. Packet Too Long	none	1. Bit Sync
20	4. IPG Delay	M. Delay Done	none	0. Idle
	5. Backoff Delay	J. Delay Done	none	6. Xmt
25	5. Backoff Delay	A. Transitions Detected	none	1. Bit Sync
	6. Xmt	I. Collision Detected	Calculate Backoff Delay	7. Jam
30	6. Xmt	H. Xmt Done	none	0. Idle
	7. Jam	K. Jam Done	none	5. Backoff Delay

35

C. COLLISION DETECTION

In the currently implemented embodiment collision detection is not used. Ordinary circuits can be used to provide

this feature with the cells providing responses as set forth in IEEE802.3. Upon detecting a collision, the cell can transmit a jamming signal for one slot time to make sure that all cells on the channel detect the collision. It then ceases transmitting and
5 executes the backoff algorithm. The backoff algorithm adjusts the contention randomization interval. IEEE802.3 uses the number of collisions experienced by the packet to calculate the backoff interval. The cell network may not always have collision detection so the cell's backoff algorithm may use the protocol's
10 inferred collision to calculate the backoff interval. If the cell has collision detection, it detects a collision in the same slot in which it occurs and retries the transmission (after the backoff interval).

For cells without collision detection where a collision
15 occurs, the cell discovers it when the protocol timeout period expires. If a cell is sending a packet to multiple destinations (the normal case), it infers a collision if at the end of the protocol timeout period, no replies have been received from any of the destinations. If even one reply is received, there was no collision
20 at the transmit point and the retransmission takes place without an increased delay due to backoff. The cell then executes the backoff algorithm just as it does with collision detection, using

the inferred collision count. After the backoff interval, the cell transmits the packet.

Therefore, the difference between collision detection and collision inference is in the length of time it takes the cell to
5 discover that a collision has occurred.

D. BACKOFF ALGORITHM

The backoff algorithm used in the currently preferred embodiment is set forth in IEEE802.3 standard, a truncated binary exponential backoff. The backoff interval is an exponential
10 function of the number of collisions (detailed or inferred) since the last successful transmission. An exponential backoff algorithm gives the system the stability it needs to recover from saturation conditions. By exponentially spreading out the load in a saturated system, the algorithm allows the system to recover.
15 Backoff interval in slots = R such that R = random number linearly distributed over the interval:
$$0 < R < 2 \text{ EXP } [\min (10, n)]$$

where n = number of collisions.

20 When a cell has two transceivers attached, it transmits every packet via both transceivers. Since the transceivers access different subchannels, they will experience different load

conditions. Each transceiver is treated as a separate subchannel and has its own backoff parameters (collision count and backoff interval). The backoff parameters are "kept" by the cells, one set for each transmission.

5 The random number for the backoff algorithm is generated by one of two methods: 1. by a pseudorandom number generation algorithm seeded with the 48 bit cell ID (guaranteed to be unique as discussed), 2. by running a counter and saving the low order bits when an external event is detected.

10 The slots are equal in durations to bit rate of the last received data. Note: if each cell used its internal bit rate, slot durations would vary from cell-to-cell.

E. CONTENTION TIMER

15 Packets that have multiple routes to a destination may experience a long contention delay via one route and a shorter delay while traveling simultaneously via another route. If that contention delay is allowed to be too long, the later packet could arrive after the destination's receive sequence number has cycled back to the same sequence number in the packet. A packet could
20 thus arrive out of sequence without the ARQ protocol detecting it. To prevent this type of error, each packet uses the contention timer field (Figure 6) that is decremented by the number of slots

that the packet has waited for contention at each hop in a multihop route. When the count reaches zero, the packet is discarded.

F. ARQ PROTOCOL

5 The cell uses a sliding window protocol with a window size of 1 and modulo 2 sequence numbering (equivalent to a stop and wait protocol). The link control mechanism is very similar to the HDLC asynchronous balanced mode. The principal difference being that with 1 bit sequence numbering instead of acknowledging
10 packets with the poll/final bit set, every information packet must have an acknowledgement.

 Before the ARQ mechanism can work, a connection must be established between the two communicating devices (cell or network control devices). The connection process is described in
15 the "connection" section later in this application. The ARQ mechanism only operates when the cell is in the connect state. The ARQ states may be considered as substates of the connect state.

 When a cell transmits a message, it waits for a reply from
20 the destination. If the cell does not receive an acknowledgement within a predefined time out period, it assumes that the message was lost and it transmits the message again.

Two types of packet may be used to carry an acknowledgement, an acknowledgement-only packet or an information packet. The acknowledgement is carried in the receive sequence number of the packet. The acknowledgement-only packet has no message field and is identified by the ACK command in the link command field. An information packet does contain a message field and is identified by the INFO command in the link command field.

Figure 25 is the link level ARQ state diagram and along with the following table, defines the various ARQ states.

	State	Event	Action	Next State
15	0: Idle	Message to Send	Build Packet	1. Idle
	0: Idle	Packet to Transmit	Send Packet	1. Contention
	0: Idle	Packet Received	Process Packet	1. Idle
	1. Contention	Packet Transmitted	Start Timer	2. Wait ACK
20	2. Wait ACK	Timeout	Stop Timer Build Packet	2. Wait ACK
	2. Wait ACK	Packet to Retransmit	Retransmit Packet	1. Contention
	2. Wait ACK	ACK pkt Received or N retries	Stop Timer	0. Idle
25	2. Wait ACK	Non ACK pkt Received	Process Packet	2. Wait ACK

A cell must store a transmit sequence number for each addressee with whom it communicates. An addressee can be a cell, a group, or a control device. For receiving, a cell must save

the receive sequence number of each source from which it receives. A source can be a cell, a group, or a control device. When a cell receives a message, it checks the CRC on the message. If the CRC is not valid, the cell does not reply to the message. If the CRC is valid, the cell does not reply to the message. The cell receiving a message also checks the message's sequence number. If the sequence number indicates that this is a duplicate packet, the cell acknowledges the receipt of the packet to the sender but does not pass the packet to the application software.

10 The ARQ protocol uses a bit that means "this is a retransmission by the sender". A receiver will not acknowledge a duplicate message unless the message has its retransmit bit on. The cell saves the sequence number for the last received message for each group for which it is a listener. It has a separate 1 bit transmit sequence number and 1 bit receive sequence number for messages addressed with the cell address (used when communicating with control devices).

20 Cell to cell communications is via group addresses. Direct addressing with cell addresses is used for network control functions. The cell will be communicating with a grouping device or network controller in those cases. A cell can have only one conversation at a given time that uses cell

addresses because it has provisions to store only one set of those sequence numbers.

When a control device wishes to communicate with a cell, it opens communications by sending a packet with a connect
5 command in the link control field. That command initializes the sequence numbers. After receipt of that command, the cell will not accept messages addressed to it (via cell address) by another control device until the conversation ends. The conversation ends when the control device sends the cell a
10 disconnect command.

The period of time that the cell waits for an acknowledgement of a message depends on the type of routing used. In general, the cell allows enough time for the packet to arrive at its destination, plus protocol processing time in the
15 destination cell and the transit time for the return packet carrying the acknowledgement.

The protocol timeout period for multihop packets is also influenced by the collision count. Even in very noisy environments, it is more likely that the reason a packet failed to
20 reach its destination in time is due to a contention rather than a transmission error. When a packet is retried, it is assumed that the collision count is an indication of system load and the

expected contention delay for a multihop packet. The delay period for multihop packets is adjusted upward as a function of collision count. The timeout period is therefore a function of the transmission baud rate, the number of hops and the collision
5 count.

G. LINK CONTROL COMMANDS

Link control commands control the operation of the ARQ protocol and the link connection process (see next section). The link command field of a packet always contains a link command.

10 ARQ Protocol Commands

INFO	Information Packet (requires acknowledgement)
ACK	Acknowledgement Only Packet (does not require acknowledgement)

15 Connection Control Commands

CONN	Connect
DISC	Disconnect
SI	Set Initialization
20 XND	Exchange Network Data

Replies to Connection Control Commands

CMDR	Command reject
25 FD	Request Disconnect
RI	Request Initialization
UA	Unnumbered Acknowledge

Only packets with the ACK and INFO commands use sequence numbering. The INFO packets have two sequence numbers, a transmit sequence number and the sequence number of the last packet received. ACK packets have both sequence number fields but the transmit sequence number is ignored by the
5 destination.

Packets with commands other than ACK or INFO are called unnumbered packets. Unnumbered packets are acknowledged in a stop and wait fashion via a UA command. Unnumbered packets do not contain a message field.

H. CONNECTION CONTROL

10 Before a control device can communicate with a cell, it must establish a connection with the cell. Establishing a connection consists of initializing the sequence numbers and putting the control device and cell into a known state. The connection establishment and maintenance procedures are governed by state machines implemented in software.

15 An announcer cell must establish a connection with each listener cell in its group. Only when the connections have been established may the announcer communicate with the listeners. Connections are controlled by a subset of the link control commands. Commands are issued by a primary station. A secondary station receives a command and sends a reply to the
20 primary. In a group, the primary station is the announcer. The listeners are secondaries. When a network control device communicates with a cell, the control device is the primary, the cell is the secondary. The link

control commands and their responses are shown below. The INFO and ACK commands are ARQ protocol commands; the rest are connection control commands.

5	Primary Command	Secondary Response	Description
	INFO		Information: valid only in connect state.
10		INFO ACK	Information: valid only in connect state. Acknowledgement: use sequence numbers in packet but do not update receive sequence number.
		CMDR	Command reject: sent only by Secondary in Connect State. Rebuild pkt and send it again.
15		RI	Request Initialization: Init secondary.
		RD DM	disconnect secondary. Request Disconnect: disconnect the secondary. Secondary is in the Disconnect state
20	ACK		Acknowledgement
		CMDR	Command reject: sent only by secondary in connect state. Rebuild pkt and send it again.
		RI	Request Initialization: Init secondary.
25		DM	disconnect secondary. Connect secondary.
	CONN		Disconnect Mode: Secondary is in the disconnect state.
30		UA CMDR	Connect Unnumbered ACK: Command reject: sent only by Secondary in connect state retry CONN:
		RI	Request Initialization: Init secondary.
35		RD	disconnect secondary, connect secondary.
	DISC		Request disconnect: send DISC.
40		UA CMDR	Disconnect Unnumbered ACK Command reject: sent only by secondary in-connect state. Retry DISC.

5	SI	CMDR	Set Initialization Command reject: Sent only by secondary in Connect State. Retry SI.
		UA	Unnumbered ACK.
10	XND		Exchange ID & Network data: This command is sent only in when the primary is in the disconnect state.
		XND	Exchange ID & Network data: The secondary sends an XND response only if it is in the disconnect state. If it receives an XND while in any other state, the secondary responds with CMDR.
		CMDR	Command reject: sent only by secondary in connect state. Disconnect secondary; then try XND again.
15			

The connection state diagrams of Figures 26 and 27 refer to primary and secondary stations. The primary station controls the connection. The secondary can request that the state of the connection change but the secondary cannot change the connection unless commanded to do so by the primary station.

PRIMARY STATION CONNECTION STATES

25	State	Event	Action	Next State
	0. Start	Power Up	Initialize	4. Wait Init
30	1. Disconnect	Connect Request	Send CONN	2. Wait Connect
	1. Disconnect	Fatal Error or RI	Send SI	4. Wait Init
	1. Disconnect	XND	Process XND	1. Disconnect
	1. Disconnect	INFO, ACK	Retry DISC	1. Disconnect
	1. Disconnect	UA, DM	Ignore	1. Disconnect
35	1. Disconnect	RD, CMDR	Retry DISC	1. Disconnect
	2. Wait Connect	UA	Reset Seq Nums	3. Connect
	2. Wait Connect	Fatal Error or RI	Send SI	4. Wait Init
	2. Wait Connect	Nonfatal error, RD, or CMDR	Send DISC	5. Wait Disc.

5	2. Wait connect	INFO, ACK	Send DISC	5. Wait Disc.
	2. Wait Connect	DM	Retry CONN	3. Wait Connect
	2. Wait Connect	XND	Send DISC	5. Wait Disc.
	2. Wait Connect	Time out	Retry CONN	2. Wait Connect
10	3. Connect	Fatal Error or RI	Send SI	4. Wait Init.
	3. Connect	Nonfatal error, RD, or disc. request	Send DISC	5. Wait Disc.
	3. Connect	DM	Send DISC	1. Disconnect
	3. Connect	CMDR, INFO,ACK	ARQ Processing	3. Connect
15	3. Connect	XND	Send DISC	5. Wait Disc.
	3. Connect	UA	Send DISC	5. Wait Disc.
	4. Wait Init	UA received	Send DISC	5. Wait Disc.
	4. Wait Init	CMDR received	Retry SI	4. Wait Init
20	4. Wait Init	INFO, ACK	Retry SI	4. Wait Init
	4. Wait Init	RD, DM,RI,XND	Retry SI	4. Wait Init
	4. Wait Init	Time out	Retry SI	4. Wait Init
	4. Wait Init			4. Wait Init
25	5. Wait disc	UA, DM		1. Disconnect
	5. Wait disc	RI	Send SI	4. Wait Init
	5. Wait disc	Fatal error	Send SI	4. Wait Init
	5. Wait disc	CMDR, RD, XND	Retry DISC	5. Wait Disc.
	5. Wait Disc	INFO, ACK	Retry DISC	5. Wait Disc.
	5. Wait Disc	Time out	Retry DISC	5. Wait Disc.

SECONDARY STATION CONNECTION STATES

30	State	Event	Action	Next State
	0 Start	Power Up	Initialization	3. Initialize
35	1. Disconnect	CONN received	Send UA	2. Connect
	1. Disconnect	SI received	Initialization	3. Initialize
40	1. Disconnect	Fatal Error	Send UA	4. Wait Init.
	1. Disconnect	XND	Send RI	1. Disconnect
	1. Disconnect	INFO, ACK	Send XND	1. Disconnect
	1. Disconnect	DISC	Retry DM	1. Disconnect
45	2. Connect	SI received	Retry DM	1. Disconnect
	2. Connect		Initialization	3. Initialize
			Send UA	
	2. Connect	DISC received	Send UA	1. Disconnect

5	2. Connect	Fatal Error	Send RI	4. Wait Init.
	2. Connect	Nonfatal error	Send RD	5. error
	2. Connect	INFO, ACK	ARQ Processing	2. Connect
	2. Connect	CONN	Retry UA	2. Connect
	2. Connect	XND	Send RD	5. Error
10	3. Initialize	DISC received	Send UA	1. Disconnect
	3. Initialize	INFO, ACK, CONN	Retry RI	3. Initialize
	3. Initialize	SI	Retry UA	3. Initialize
	3. Initialize	XND	Retry RD	3. Initialize
15	4. Wait Init.	SI received	Initialization	3. Initialize
	4. Wait Init	INFO, ACK	Send UA	4. Wait Init
	4. Wait Init	DIS C,XND,CONN	Retry RI	4. Wait Init
	4. Wait Init	DIS C,XND,CONN	Retry RI	4. Wait Init
20	5. Error	DISC received	Send UA	1. Disconnect
	5. Error	SI received	Initialization	3. Initialize
	5. Error	SI received	Send UA	3. Initialize
	5. Error	SI received	Send UA	3. Initialize
25	5. Error	INFO, ACK	Retry RD	5. Error
	5. Error	CONN,XND	Retry RD	5. Error

25 NOTE: Retries: A reply may be retried N times. The event that causes retry N+1 is defined to be a fatal error and causes initialization. The cell maintains one retry count and it is incremented when any reply other than INFO or ACK is retried. The retry count is cleared whenever a non-retry reply is sent to the

30 primary cell.

I. ABORT SEQUENCE

A cell transmitting a packet can abort the packet by

35 transmitting an abort sequence instead of continuing to transmit

the packet. The Abort sequence is a group of at least 12 ones transmitted in succession. A receiving cell identifies an abort from the code verifier of Figure 16. A receiving packet treats any 3 of 6 code violation as an abort. One result of this is that a link
5 idle condition results in an abort. If the link is idle (no transitions) for more than a bit time, the result is a code violation. When a cell receiving a packet detects an abort sequence, it discards the portion of the packet that it has clocked in and begins searching for a new packet preamble. The abort
10 sequence is also used for jamming after a collision is detected.

J. SYSTEM ID

Referring to Figure 29, the method by which the 48 bit system ID is used within the packets is illustrated. Thirty-two bits of the system ID shown as field 251 is placed directly into
15 the packet as indicated by the field 255. The remaining 16 bits are used in the calculation of the packet CRC. Initially, the CRC register begins with all ones as indicated by the field 252 at the start of the CRC calculation. Then the 16 bit field 250 of the system ID is used in the CRC calculation to provide a 16 bit field
20 253. The field 253 is stored in the EEPROM and used as a preset CRC field each time a packet CRC is calculated.

When a packet is to be transmitted once the preset field is stored, the stored CRC field is coupled to the CRC register. The 16 bit packet CRC field is calculated using this present field and the other fields in the packet used to calculate the packet CRC. (All
5 fields except the contention timer field are used.) The other 32 bits of the system ID are transmitted within the packet.

When a packet is received, the processor calculates a CRC for the received packet by first placing its stored CRC preset field in its CRC register and then computing the packet CRC (again, the
10 contention timer field is not used). If the newly computed CRC field does not match the field in the packet, it is assumed that the packet has been improperly transmitted or that the transmitted packet, if correct received, has a different system ID and thus should be discarded.

15

VI. GROUPING DEVICE

The grouping device can take various forms and can be realized with commercially available hardware such as a personal computer. These computers can be readily programmed to perform the various functions described in the application performed by
20 the grouping device. For example, they can be readily programmed to provide the packets needed to communicate with the cells for grouping. Other functions such as the generation of the random

number used within the packets can be generated with well-known programs.

An Apple II computer, for instance, may be used as a grouping device. The 48 bit system ID may be stored on a disk; or, a printed circuit card may be provided which engages one of the slots of the Apple II computer, the card can contain the system ID which is taken from a cell such as cell 232 of Figure 28. As groups are formed, the assigned group numbers, member numbers, etc., can be stored on the disk or stored in an EEPROM on a card.

10 In Figure 28, the elements of a presently preferred grouping device are illustrated. They include a CPU 226 which may be an ordinary microprocessor. The CPU communicates with a memory which may comprise a RAM 227, ROM 228 and storage means 229 for storing the system ID. Where a floppy disk is used the system ID and program (otherwise stored in ROM 228) are stored on the disk, with the program being transferred to RAM for execution.

A display means 230 such as a ordinary monitor is coupled to the CPU to provide a display to the user, for instance, the display can be used to provide lists of the groups with their ASCII names. A keyboard 231 is used to allow commands to be entered into the CPU.

The CPU is shown coupled to a cell 232 with the cell being coupled to a network through transceiver 233. The cell 232 is part of the grouping devices and the cell's ID is used by the grouping devices as a system ID. Typical messages transmitted by the computer to the cell are shown in Appendix B, for example, the message of assigning the destination cell to be an announcer in a designated group is a message generated by the grouping device. The grouping device can communicate directly with the cell over one of the three pairs of leads which are coupled to the I/O subsections or through the select pin which allows messages from the CPU 226 to be read to the fourth I/O subsection.

Thus, a network for sensing, communicating and controlling which has distributed intelligence has been described. While in this application a simple example of use of cells in a home environment has been described, it will be obvious to one skilled in the art that the disclosed invention may be used in numerous other applications. Appendix C to this application contains a list of some other applications in which the present invention may be used.

CLAIMS

5 1. A network for sensing, communicating and controlling comprising:

 a plurality of programmable cells, each of which includes a permanent, unique identification number (cell ID);

 each of said cells being assigned to perform at least one of
10 the functions of sensing, communicating or controlling in said network;

 groups of said cells being programmed to perform group functions within said network each of said cells in a given group being assigned a group identification number (group ID), the
15 information needed to carry out said group function being programmed into and distributed among said cells in said group;

 said cells communicating with one another over at least one medium using said cell IDs and group IDs;

 whereby a network for sensing, communicating and
20 controlling is realized.

2. The network defined by Claim 1 wherein all of said cells in said network are assigned the same system identification number (system ID).

5 3. The network defined by Claim 1 (first network) and a second network as defined by Claim 2, said first and second networks having different system IDs, and a communication means for connecting said network and for converting one of said system IDs to the other of said system IDs.

10

4. In a network for sensing, communicating and controlling which comprises a plurality of cells, a method for establishing a communication link between a first cell and a second cell comprising the steps of:

15 determining the unique identification number (ID) assigned to each of said cells;

 broadcasting a first packet from said first cell which includes the IDs of said first cell and said second cell;

 rebroadcasting a modified first packet by each of said cells
20 other than said first cell and said second cell receiving said first packet, said rebroadcasted modified first packet including the ID of each cell rebroadcasting said first packet;

receiving said modified first packet by said second cell and replying to said modified first packet with a reply packet, said reply packet including the IDs of said rebroadcasting cells included in said modified first packet;

5 receiving said reply packet by said first cell;

assigning said rebroadcasting cells as repeaters, thereby forming a communications link between said first and second cells.

10 5. The steps defined by Claim 4 including the step of assigning said first cell the task of sensing a condition and broadcasting predetermined messages when said condition changes.

15 6. The method defined by Claim 5 including the steps of assigning said second cell the task of controlling an object upon receipt of said predetermined messages from said first cell and preparing and transmitting acknowledgements to said first cell upon receipt of said predetermined messages.

20

7. A network for sensing, communicating and controlling comprising:

a plurality of cells each of said cells including (1) a unique identification number (cell ID), (2) a processor for operating upon messages, said processor of each of said cells having access to its respective cell ID, and (3) an input/output (I/O) section for
5 coupling messages between its respective processor and a communications medium;

grouping means for causing at least two of said cells to cooperate with one another as members of a group in the performance of a group function, said grouping means
10 establishing said membership by employing said cell IDs and by assigning said cells a group identification number (group ID) and tasks needed to carry out said group function;

said cells of said group communicating with one another over said medium by using said group IDs with their respective
15 processors operating upon messages to carry out their respective said tasks;

whereby a network for sensing, communicating and controlling is realized.

20 8. The network defined by Claim 7 wherein said cells in said network are assigned the same system ID and communicate with one another using the same system ID and said group ID.

9. A network for sensing, communicating and controlling comprising:

5 a plurality of cells each of said cells including (1) a unique identification number (ID), (2) a processor for operating upon messages, said processor of each of said cells having access to its respective ID, and (3) an input/output (I/O) section for coupling messages between its respective processor and a communications medium;

10 grouping means for causing at least a first and second of said cells to cooperate with one another as members of a first group in the performance of a first group function, said grouping means establishing said membership in said first group by employing IDs of said first and second cells, and by assigning said
15 first and second cells a first group identification number (group ID) and tasks needed to carry out said first group function;

said first and second cells communicating with one another over said medium by using said first group IDs for carrying out their respective tasks through their respective processors by
20 operating upon messages communicated between said first and second cells;

said grouping means for causing at least a third and fourth of said cells to cooperate with one another as members of a second group in the performance of a second group function, said grouping means establishing said membership in said second group by employing IDs of said third and fourth cells, and by assigning said third and fourth cells a second group ID and tasks needed to carry out said second group function;

said third and fourth cells communicating with one another over said medium by using said second group ID for carrying out their respective tasks through their respective processors by operating upon messages communicated between said third and fourth cells,

whereby a network for sensing, communicating and controlling is realized.

15

10. The network defined by Claim 9 wherein said first cell of said first group is assigned a task of announcing and said second cell in said first group is assigned the task of listening.

20

11. The network defined by Claim 10 wherein said third cell is assigned the task of sensing and said fourth cell is

assigned the task of controlling and wherein a fifth cell is assigned the task of repeating messages for said second group.

12. A network for sensing, communicating and controlling
5 comprising:

a first programmable cell comprising a semiconductor integrated circuit having a processor and an input/output (I/O) section coupled to its processor, said first cell being assigned a first system identification number (first system ID) and a first
10 unique cell ID number (first cell ID), said first cell's processor for preparing and acting upon predetermined messages which are coupled to a communications medium through said first cell's I/O section, said first cell's I/O section being coupled to a sensing means for sensing a condition, said first cell being assigned a
15 first group identification number (group ID);

a second programmable cell comprising a semiconductor integrated circuit having a processor and an I/O section coupled to its processor, said second cell being assigned said first system ID and a second unique cell ID said second cell's processor
20 for preparing and acting upon said predetermined messages and for coupling said messages through its I/O section to medium,

said second cell being coupled to control means for controlling an object, said second cell being assigned said first group number;

said first and second cells communicating with one another over said medium through their respective I/O sections by using
5 said first system ID, their first and second cell ID's and said group ID;

whereby a sensing, communicating and control network is realized.

10 13. The network defined by Claim 12 including a third programmable cell comprising a semiconductor integrated circuit having a processor and an I/O section coupled to its processor, said third cell being assigned said first system ID and a third unique cell ID, said third cell's processor for preparing and acting
15 upon messages, said third cell being assigned the task of repeating said predetermined messages transmitted between said first and second cells, said third cell being assigned said first group ID.

20 14. The network defined by Claim 12 or 13 including a fourth programmable cell comprising a semiconductor integrated circuit having a processor and an I/O section coupled to its

respective processor said fourth cell being assigned said first system ID and a fourth unique cell ID, said fourth cell's processor for preparing and acting upon predetermined messages, said fourth cell being assigned said first group ID and being coupled to
5 a second control means for controlling a second object.

15. A cell for use in a network which provides sensing, communications and control comprising:

- a processing means having multiple processors for
10 preparing messages for broadcast over said network and for interpreting messages received from said network, said processing means including storage means for storing at least one computer program which is executed by said processing means;
- 15 an input and output section having a plurality of subsections for:
 - coupling messages between said processing means and said network;
 - providing at least one of the functions of sensing and
20 controlling;
 - coupling means for coupling any one of said multiple processors to any one of said input/output

subsections such that said processing means interfaces with said input/output section without interrupting the execution of said program in ones of said processors executing said program;

5 whereby a cell for use in a network which provides sensing, communications and control is realized.

16. The cell defined by Claim 15 wherein said cell is fabricated on a single substrate as an integrated circuit.

10

17. The cell defined by Claim 16 wherein said memory includes a programmable memory.

18. The cell defined by Claims 15 or 17 wherein said cell
15 includes storage means for storing a unique cell identification number.

19. The cell defined by Claim 18 wherein said cell identification number is a 48 bit binary number.

20

20. The cell defined by Claim 15 wherein said input/output section includes an analog-to-digital converter and a digital-to-analog converter.

5 21. The cell defined by Claim 20 wherein said cell is fabricated on a single substrate as an integrated circuit.

22. The cell defined by Claim 21 wherein said cell includes storage means for storing a unique cell identification
10 number.

23. The cell defined by Claim 22 wherein said cell identification number is a 48 bit binary number.

15 24. A network for sensing, communicating and controlling comprising:

at least one communications medium;

a first plurality of programmable cells coupled to said medium for transmitting and receiving first messages over and
20 from said medium, each of said first said cells having a unique cell identification number (cell ID), all of said first cells having a first group identification number (group ID), one of said first

cells being programmed to sense a first condition and to prepare one of said first messages in response to said first condition and another of said first cells being programmed to control a first object in response to said one of said first messages, said first
5 cells communicating with one another over said medium by using one of said first cell's IDs and said first group ID;

a second plurality of programmable cells coupled to said medium for transmitting and receiving second messages over and from said medium, each of said second cells having a unique cell
10 ID, all of said second cells having a second group ID, one of said second cells being programmed to sense a second condition and to provide one of said second messages in response to said second condition and another of said second cells being programmed to control a second object in response to said one of said second
15 messages, said second cells communicating with one another over said medium by using one of said second cell's IDs and said second group ID;

a third programmable cell coupled to said medium having a unique cell ID, and having said first group ID, said third cell for
20 performing one of the functions of sensing or controlling by employing said first messages, said third cell having said second group ID for purposes of repeating said second messages;

whereby a network for sensing, communicating and controlling is realized.

25. The network defined by Claim 24 wherein said first
5 cells, second cells and third cell have a common system
identification number.

26. The network defined by Claim 25 wherein said first
cells, second cells and third cell are each an integrated circuit.
10

27. The network defined by Claim 26 wherein each of said
first cells, second cells and third cell includes a processor and an
input/output section for coupling said processor to said medium.

15 28. The network defined by Claim 27 wherein each of said
input/output sections includes an analog-to-digital converter and
a digital-to-analog converter.

29. The network defined by Claims 24 or 28 wherein said
20 other of said first cell sends an acknowledgement message in
response to said one of said first messages.

30. The network defined by Claim 29 wherein said other of said second cells sends an acknowledgement message in response to said one of said second messages.

5 31. A cell for a network which network provides for the sensing of conditions, communicating at least one message on said conditions and controlling at least one object based on said message, comprising:

 a processor for preparing a packet containing said message;
10 interface means for interfacing between said processor and said network and for sensing said condition;

 said processor for encoding said packets into segments of 6 bit codes, each segment containing 3 binary ones and 3 binary zeroes (3-of-6 codes);

15 whereby a cell is realized.

32. The cell defined by Claim 31 wherein said cell includes a unique identification number.

20 33. The cell defined by Claims 31 or 32 wherein a predetermined one of said 3-of-6 codes is used as a preamble for said packet.

34. The cell defined by Claim 33 wherein said cell is fabricated on a single semiconductor substrate.

5 35. The cell defined by Claim 34 wherein said interface means includes an analog-to-digital converter and a digital-to-analog converter.

36. A cell for a network which network provides for the
10 sensing of a condition, communicating at least one message on said condition and controlling at least one object comprising:

· a processor for receiving and interpreting a packet containing said message;

interface means for interfacing between said processor and
15 said network and for controlling said object;

said processor including means coupled to receive said packet for converting segments of 6 bit codes, where each group contains 3 binary ones and 3 binary zeroes (3-of-6 codes) into 4 bit nibbles;

20 whereby a cell is realized.

37. The cell defined by Claim 36 wherein said cell includes a unique identification number.

38. The cell defined by Claims 36 or 37 including means for
5 synchronizing said processor to a predetermined one of said 3-of-
6 codes.

39. The cell defined by Claim 38 wherein said cell is fabricated on a single semiconductor substrate.

10

40. The cell defined by Claim 39 wherein said interface means includes an analog-to-digital converter and digital-to-analog converter.

15 41. A cell for a network which network provides for the sensing of conditions, communicating messages on said conditions and controlling objects based on said messages comprising:

a processor for preparing and interpreting said messages,
20 interface means for interfacing between said processor and said network and for performing at least one of the functions of sensing one of said conditions or controlling one of said objects;

said processor encoding said messages into segments of 6 bit codes, each group containing 3 binary ones and 3 binary zeroes (3-of-6 codes), and means for converting groups of 6 bit codes received over said network into 4 bit nibbles;

5 whereby a cell is realized.

42. The cell defined by Claim 44 wherein said cell includes a unique identification number.

10 43. The cell defined by Claims 41 or 42 wherein a predetermined one of said 3-of-6 codes is used as a preamble for packets containing said messages.

15 44. The cell defined by Claim 43 wherein said cell is fabricated on a single semiconductor substrate.

20 45. The cell defined by Claim 44 wherein said interface means includes an analog-to-digital converter and digital-to-analog converter.

46. A network for sensing, communicating and controlling having a plurality of cells which communicate with one another through packets;

a first plurality of said cells being coupled to sense conditions and for transmitting packets indicating a change in said conditions (announcer cells);

a second plurality of said cells being coupled to control objects in
5 response to predetermined ones of said packets (listener cells);

at least one of said announcer cells and listener cells also performing the function of repeating at least some of said packets (repeater cells);

a first group of cells being programmed with a first group identification number (group ID), said first group including at least one of said announcer
10 cells, one of said listener cells and one of said repeater cells;

a second group of cells being programmed with a second group ID, said second group including at least one of said announcer cells, one of said listener cells and repeater cells;

said first group of cells communicating among themselves with first
15 packets, said first packets being initiated and acted upon only by cells in said first group;

said second group of cells communicating among themselves with second packets, said second being initiated and acted upon only by cells in said second group,

20 whereby communications in said network are limited to groups formed in said network.

47. The network defined in Claim 46 wherein each of said announcer cells and listener cells are associated with one or more groups with each group being identified with a different group ID, however, where each of said announcer cells announce group ID for only a single one of said groups.

5

48. A cell for use in a network which provides for sensing, communicating and controlling, comprising:

a processor for preparing and interpreting packets;

interface means for interfacing between said processor and said

10 network;

said processor for encoding said packets into segments of 6 bit codes, each segment containing 3 binary ones and 3 binary zeroes (3-of-6 codes) and for decoding packets having said 3-of-6 coding;

said interface means for utilizing a first one of said
15 segments for synchronization;

whereby a cell is realized.

49. The cell defined by Claim 48 wherein said first segment comprises alternate binary ones and binary zeroes.

20

50. The cell defined by Claim 49 wherein said encoding and decoding includes the following conversion:

159

	<u>3-of-6 Code</u>	<u>4 Bit Nibble</u>
	011010	0000
	001101	0001
5	001110	0010
	001011	0011
	011100	0100
	011001	0101
	010110	0110
10	010011	0111
	101100	1000
	100101	1001
	100110	1010
	100011	1011
15	110100	1100
	110001	1101
	110010	1110
	101001	1111

160

Appendix A, Packet Examples

Routing Types for Packet Examples

- 1 Fully Addressed
- 2 Open Flooding
- 3 Restricted Flooding
- 4 Group Flooding

NOTE: The packet sizes are in cell memory bits (before 3-of-6 encoding). A packet on a communications subchannel, after conversion to 3 of 6 code, is 50% larger.

Single Hop

Packet Format:

Preamble, 16 bits
Flag, 4 bits
Destination cell Address, 48 bits
Contention Timer, 10 bits
Contention Timer Checksum, 6 bits
Hop Count, 4 bits
Randomizer, 8 bits
Link Control
Retransmit Flag, 1 bit
Rcv Seq, 1 bit
Xmt Seq, 1 bits
Unused, 1 bit
Command, 4 bits
Network Control
Routing Type, 4 bits = 1 (Fully Addressed)
Source Cell Address, 48 bits
Message, 16 to 512 bits
Message Type, 8 bits
Message Contents, 8 to 511 bits
Encryption Check, 16 bits
CRC, 16 bits
Flag, 4 bits

161

Single Hop

Reply Format:

Preamble, 16 bits
Flag, 4 bits
System ID, 32 bits
Destination Cell Address, 48 bits
Contention Timer, 10 bits
Contention Timer Checksum, 6 bits
Hop Count, 4 bits
Randomizer, 8 bits
Link Control
Retransmit Flag, 1 bit
Rcv Seq, 1 bit
Xmt Seq, 1 bits
Unused, 1 bit
Command, 4 bits
Network Control
Routing Type, 4 bits = 1 (Fully Addressed)
Source Cell Address, 48 bits
Encryption Check, 16 bits
CRC, 16 bits
Flag, 4 bits

162

Multihop Full Address

Packet Format:

Preamble, 16 bits
Flag, 4 bits
System ID, 32 bits
Next Cell Address, 48 bits
Contention Timer, 10 bits
Contention Timer Checksum, 6 bits
Hop Count, 4 bits
Randomizer, 8 bits
Link Control
Retransmit Flag, 1 bit
Rcv Seq, 1 bit
Xmt Seq, 1 bits
Unused, 1 bit
Command, 4 bits
Network Control
Routing Type, 4 bits = 1 (Fully Addressed)
Cell Address List
 Address Count, 4 bits
 Addresses, 48 - 768 bits
Source Cell Address, 48 bits
Message, 16 to 512 bits
Message Type, 8 bits
Message Contents, 8 to 511 bits
Encryption Check, 16 bits
CRC, 16 bits
Flag, 4 bits

163

Multihop Full Address

Reply Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Destination Cell Address, 48 bits

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 1 (Fully Addressed)

Cell Address List

Address Count, 4 bits

Addresses, 48 - 768 bits

Source Cell Address, 48 bits

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

164

Open Flooding

Packet Format:

Preamble, 16 bits
Flag, 4 bits
System ID, 32 bits
Broadcast Address, 48 bits = All Zeros
Contention Timer, 10 bits
Contention Timer Checksum, 6 bits
Hop Count, 4 bits
Randomizer, 8 bits
Link Control
Retransmit Flag, 1 bit
Rcv Seq, 1 bit
Xmt Seq, 1 bits
Unused, 1 bit
Command, 4 bits
Network Control
Routing Type, 4 bits = 2 (Open Flooding)
Destination Cell Address, 48 bits
Source Cell Address, 48 bits
Message, 16 to 512 bits
Message Type, 8 bits
Message Contents, 8 to 511 bits
Encryption Check, 16 bits
CRC, 32 bits
Flag, 4 bits

165

Open Flooding

Reply Format:

Preamble, 16 bits
Flag, 4 bits
System ID, 32 bits
Broadcast Address, 48 bits = All Zeros
Contention Timer, 10 bits
Contention Timer Checksum, 6 bits
Hop Count, 4 bits
Randomizer, 8 bits
Link Control
Retransmit Flag, 1 bit
Rcv Seq, 1 bit
Xmt Seq, 1 bits
Unused, 1 bit
Command, 4 bits
Network Control
Routing Type, 4 bits = 2 (Open Flooding)
Destination Cell Address, 48 bits
Source Cell Address, 48 bits
Encryption Check, 16 bits
CRC, 16 bits
Flag, 4 bits

166

Restricted Flooding

Packet Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Broadcast Address, 48 bits = All Zeros

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 3 (Restricted Flooding)

Destination Cell Address, 48 bits

Source Cell Address, 48 bits

Message, 16 to 512 bits

Message Type, 8 bits

Message Contents, 8 to 511 bits

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

167

Restricted Flooding

Reply Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Broadcast Address, 48 bits = All Zeros

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 3 (Restricted Flooding)

Destination Cell Address, 48 bits

Source Cell Address, 48 bits

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

168

Group Announcement

Packet Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Group Address, 48 bits

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 4 (Group Flooding)

Source Member Number, 8 bits

Destination Member Number, 8 bits, (0 = broadcast)

Message, 16 to 512 bits

Message Type, 8 bits

Message Contents, 8 to 511 bits

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

169

Group Announcement

Reply Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Group Address, 48 bits

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 4 (Group Flooding)

Source Member Number, 8 bits

Destination Member Number, 8 bits

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

170

Probe

Packet Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Broadcast Address, 48 bits = All Zeros

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 3 (Restricted Flooding)

Destination Cell Address, 48 bits

Source Cell Address, 48 bits

Message, 49 to 769 bits

Message Type, 8 bits

Message Contents, 48 to 768 bits (Route List)

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

171

Probe

Reply Format:

Preamble, 16 bits

Flag, 4 bits

System ID, 32 bits

Broadcast Address, 48 bits = All Zeros

Contention Timer, 10 bits

Contention Timer Checksum, 6 bits

Hop Count, 4 bits

Randomizer, 8 bits

Link Control

Retransmit Flag, 1 bit

Rcv Seq, 1 bit

Xmt Seq, 1 bits

Unused, 1 bit

Command, 4 bits

Network Control

Routing Type, 4 bits = 3 (Restricted Flooding)

Destination Cell Address, 48 bits

Source Cell Address, 48 bits

Message Field,

Message Type 8 bits

Message contents, Route List

Encryption Check, 16 bits

CRC, 16 bits

Flag, 4 bits

172

Broadcast Command

Packet Format:

- Preamble, 16 bits
- Flag, 4 bits
- System ID, 32 bits
- Broadcast Address, 48 bits = All Zeros
- Contention Timer, 10 bits
- Contention Timer Checksum, 6 bits
- Hop Count, 4 bits
- Randomizer, 8 bits
- Link Control
- Retransmit Flag, 1 bit
- Rcv Seq, 1 bit
- Xmt Seq, 1 bits
- Unused, 1 bit
- Command, 4 bits
- Network Control
- Routing Type, 4 bits = 3 (Restricted Flooding)
or 2 (Open Flooding)
- Source Address, 48 bits
- Message, 16 to 512 bits
- Message Type, 8 bits
- Message Contents, 8 to 511 bits
- Encryption Check, 16 bits
- CRC, 16 bits
- Flag, 4 bits

Broadcast Command

Reply Format:

NO REPLY

173

Appendix B - Message Types

Probe

Function: Determine the best route from the announcer to the listener.

Source: Group Announcer

Address Type: Cell

Routing Method: Restricted Flooding

Message Type: 2 (Number for 8 bit field)

Message Content: Address Count (1 byte), (number of cell IDs in probe packet - this is the number of cells rebroadcasted packet)

Address List

Probe Result

Function: report the address list in the first probe packet received by the destination Cell.

Source: Cell previously addressed by a Probe message.

Address Type: Cell

Routing Method: Restricted Flooding

Message Type: 3

Message Content: Address Count (1 byte), Address List

Assign Group Announcer

Function: Assign the destination Cell to be an announcer in the designated group.

Source: Grouping Device

Destination: Cell

Address Type: Cell or Group Member

Routing Method: Restricted Flooding or Group Flooding

Message Type: 4

Message Content: Group Number, Member Number

Deassign Group Announcer

Function: Deassign the destination Cell from serving as an announcer in the designated group.

Source: Grouping Device

174

Destination: Announcer Cell
Address Type: Cell or Group Member
Routing Method: Restricted Flooding or Group Flooding
Message Type: 5
Message Content: none

Assign Group Listener

Function: Assign the destination Cell to be a listener in the designated group.

Source: Grouping Device
Destination: Cell
Address Type: Cell or Group Member
Routing Method: Restricted Flooding or Group Flooding
Message Type: 6
Message Content: Group Number, Member Number

Deassign Group Listener

Function: Deassign the destination Cell from serving as a listener in the designated group.

Source: Grouping Device
Destination: Listener Cell
Address Type: Cell or Group Member
Routing Method: Restricted Flooding or Group Flooding
Message Type: 7
Message Content: none

Assign Group Repeater

Function: Assign the destination Cell to be a repeater in the designated group.

Source: Grouping Device
Destination: Cell
Address Type: Cell or Group Member
Routing Method: Restricted Flooding or Group Flooding
Message Type: 8
Message Content: Group Number, Member Number

Deassign Group Repeater

Function: Deassign the destination Cell from serving as a repeater in the designated group.

Source: Grouping Device
Destination: Group Repeater Cell
Address Type: Cell or Group Member
Routing Method: Restricted Flooding or Group Flooding

175

Message Type: 9
Message Content: none

Assign Repeater

Function: Assign a Cell to act as a repeater. Used to assign Cells that are not normally allowed to be a repeater, i.e. a Cell with one transceiver on a nonradiated medium.

Source: Control device

Destination: Cell

Address Type: Cell

Routing Method: Fully Addressed, Open Flooding, Restricted Flooding

Message Type: 10

Message Content: none

Shutup

Function: Broadcast message telling all Cells to stop transmitting until commanded to resume.

Source: Control Device

Destination: Cells

Address Type: Broadcast or Cell

Routing Method: Restricted Flooding or Open Flooding

Message Type: 11

Message Content: none

Report your Input

Function: Command a Cell to report its input.

Source: Cell or Control Device

Destination: Cell

Address Type: Any

Routing Method: Any

Message Type: 12

Message Content: Input number (byte).

Report your Output

Function: Command a Cell to report its output.

Source: Control Device or Cell

Destination: Cell

Address Type: Any

Routing Method: Any

Message Type: 13

Message Content: Output number (byte).

Download

176

Function: Download data or code
Source: Control Device
Destination: Cell
Address Type: Any
Routing Method: Any
Message Type: 14
Message Content: Address, length, code

Set communication parameter

Function: Set a Communication Parameter in the Cell
Source: Control Device
Destination: Cell
Address Type: Any
Routing Method: Any
Message Type: 15
Message Content: Parameter number, value

Announcement

Function: Announce Sensor Data
Source: Group Announcer
Destination: Group
Address Type: Group, Broadcast
Routing Method: Group Flooding
Message Type: 16
Message Content: 0 - 255 (one byte)

177

APPENDIX C APPLICATIONS

CATEGORY	SUBCATEGORY	APPLICATION
General Usage	Sensing Functions Communication Functions Control Functions	
Agriculture	Crop Management	Crop Sensor/Comm Irrigation Ctrl/Comm Land Leveler Sensor Comm Pest Sensor/Comm (with cell IDs identifying animals)
	Livestock	Detector/Tracker Feed Sense/Ctrl/Comm Milker Sense/Ctrl/Comm Weight Sensor/Comm Herder Signal Device
Commercial	Banking	ATM Card Electronic Money
	Commercial	Cash Register Sense/Ctrl/Comm Elevator Sense/Ctrl/Comm Slot Machine Sense/Ctrl/Comm Vending Machine Sense/Ctrl/Comm
	Commercial,Misc	Diaper Sensor/Comm Pager Ctrl/Comm Protechnics, Sensor Ctrl Stamp I.D. Watch Ctrl/
	Construction	Decay Sensor/Comm Post Sensor/Comm
	Energy Management	Sensor Sense/Comm Thermostat Ctrl/Comm Utility Sensor/Comm Vent Ctrl/Comm
	Security	Lock Sense/Ctrl/Comm Smart Keys (Serial #)
Communication	Communications	Cable Elimination Channel Ctrl/Comm Network Configuration Ctrl/Comm Cell to Anything Bridge Phone I.D. (Cell I.D.) Phone to Cell Bridge

178

Computer Network	Architecture	Telemetry Ctrl/Comm Wiring Elimination
	Peripheral	Slow Data Network Artificial Intelligence Configuration Ctrl Copy Protection Parallel Processing Nodes
Consumer	Develop. System	Cable Elimination
	Appliances	Keyboard Sense/Comm Mouse Sense/Comm Wiring Elimination Emulator Device
	Consumer, Misc	Sensor Sense/Comm Switch Sense/Ctrl/Comm
	Entertainment	Detector/Tracker (Electronic Serial #) Low Battery Detector Smart Lottery Ticket Amusement Park Ctrl'r Arcade Game Ctrl'r Cable TV Access Ctrl'r Cable TV Sample Ctrl'r CD Player Ctrl'r Special Effects Ctrl'r
	Home Improvement	Stereo Ctrl'r TV Ctrl'r VCR Ctrl'r
		Central Clock Sys Curtain Ctrl/Comm Door Sense/Comm
		Garage Door Ctrl'r Intercom Intercom Ctrl'r Pool Ctrl'r Sense/Ctrl/Comm
		Smoke/Fire Detector Window Sense/Ctrl/Comm
	Pets	Detector/Tracker (Electronic Serial #) Pet Ctrl/Trainer
		Interactive Book Sense/Ctrl/Comm Test Sense/Comm
Education	Education, Misc	DAC/ADC
Engineering	Data Acquisition	DAC/ADC
	Instrumentation	Switch Sense/Ctrl/Comm
Home	Electrical	Light Ctrl/Comm
		Receptacle Sense/Comm/Ctrl

179

		Switch Sense/Ctrl/Comm All forms of sensing All forms of control
	Energy Management	Sensor Sense/Comm Thermostat Ctrl/Comm Utility Sensor/Comm Vent Ctrl/Comm
	Home Improvement	Central Clock Sys Curtain Ctrl/Comm Door Sense/Comm Garage Door Ctrl'r Intercom Intercom Ctrl'r Pool Ctrl'r Sense/Ctrl/Comm Smoke/Fire Detector Window Sense/Ctrl/Comm
	Security	Lock Sense/Ctrl/Comm Smart Keys (Serial #) Vibration/Motion Sense/Comm Window Sense/Ctrl/Comm
	Sprinkler Sys	Timer Ctrl/Comm Valve Ctrl/Comm Witness Sense/Ctrl
Industrial	Energy Management	Sensor Sense/Comm Thermostat Ctrl/Comm Utility Sensor/Comm Vent Ctrl/Comm
	Industrial Equipment	Oil Drill Sensor/Ctrl/Comm Power Load Sense/Ctrl/Comm Utility Sensor/Comm
	Security	Lock Sense/Ctrl/Comm Smart Keys (Serial #) Vibration/Motion Sense/Comm Window Sense/Ctrl/Comm
	Security , Industrial	Copy Protection Detector/Tracker (Electronic Serial #) Personnel Badge I.D.
Law	Security, Law	Copy Protection I.D. Card (Serial #) Gun I.D. Passport (Serial #) Shoplifter Detector
Manufacturing	CIM	Artificial Intelligence Wiring Elimination




180

Production Ctrl		Detector/Tracker (Electronic Serial #)
Process Ctrl		Inventory Sense/Comm
Production Automation		Line Balance
		Production Flow/Sense
Robotics		Detector/Tracker (Electronic Serial #)
		Robot Sense/Ctrl/Comm
Medical	Medical, Misc	Bio-Feedback
		Bionics
		Handicapped Interfaces
		Heart Pacer
		Implants
		Medical Alert Sense/Comm
		Medicine Alert Sense/Comm
		Patient Monitoring
		Personal Dispenser Ctrl/Comm
		Personal Monitors
		Prosthetics
Military	Military, Misc	Copy Protection
		Damage Ctrl Sense/Comm
		Detector/Tracker (Electronic Serial #)
		Personnel Badge I.D.
		Redundant Comm
		SDI Sense/Ctrl/Comm
		Senna Buoy Sense/Comm
		Spying Sense/Ctrl/Comm
		Position Sense/Ctrl/Comm
		System Diagnostics Sense/Comm
		War Game Monitor/Sim
		Weapon Sense/Ctrl/Comm
		Lock Sense/Ctrl/Comm
		Smart Keys (Serial #)
		Vibration/Motion Sense/Comm
		Window Sense/Ctrl/Comm
Scientific		Weather/Earthquake/etc. sensor
Transportation	Automotive	General sensing
		General communication
		General control
		Anti-lock Breaking Sys
		Complex Cable Elimination
		Gauge Ctrl
		In Dash Map/Locator
		Instrument Panel Ctrl
		License Plate I.D. & Comm
		Light Ctrl/Comm

181

		Regulator Sense/Comm Smart Keys (Serial #)
		Switch Sense/Ctrl/Comm System Diagnostics Sense/Comm Wiring Elimination
Avionics		Anti-lock Breaking Sys Complex Cable Elimination Gauge Ctrl Instrument Panel Ctrl Light Ctrl/Comm Regulator Sense/Comm Sensor Sense/Comm Switch Sense/Ctrl/Comm System Diagnostics Sense/Comm Wiring Elimination
	Transportation, Misc	Emergency Locator (ELT) Sense/Comm Traffic Monitor/Ctrl Traffic Signal Sense/Ctrl/Comm 3-D "Chip-Wits" Sense/Ctrl/Comm Bingo Card Sense/Comm Game sense/Ctrl/Comm Camera Sense/Ctrl/Comm Hobby Kit Sense/Ctrl/Comm Magic Equipment Sense/Ctrl/Comm Miniature Train Ctrl/Comm Remote Ctrl Sense/Ctrl/Comm
Tpy/Hobby/Spo	Game	Emergency Locator (ELT) Sense/Comm Trap-Line Sensor Sport Accessory Sense/Ctrl/Comm Lego-Bot Sense/Ctrl/Comm Media Interactive Toy Sense/Ctrl/Comm Animated Toy Sense/Ctrl/Comm
	Hobby	
	Sport	
	Toy	

1/18

FIG 1**FIG 2****FIG 3**

SUBSTITUTE SHEET

2/18

FIG 4





FIG 5



3/18

FIG 6 GROUP PACKET FORMAT




FIG 7 DESTINATION





FIG 8 GROUP FORMATION



4/18

FIG 9

4-BIT PATTERN ASSIGNMENT	ASSIGNED 3-OF-6 PATTERN	FUNCTION
0 0 0 0	0 1 1 0 1 0	DATA
0 0 0 1	0 0 1 1 0 1	DATA
0 0 1 0	0 0 1 1 1 0	DATA
0 0 1 1	0 0 1 0 1 1	DATA
0 1 0 0	0 1 1 1 0 0	DATA
0 1 0 1	0 1 1 0 0 1	DATA
0 1 1 0	0 1 0 1 1 0	DATA
0 1 1 1	0 1 0 0 1 1	DATA
1 0 0 0	1 0 1 1 0 0	DATA
1 0 0 1	1 0 0 1 0 1	DATA
1 0 1 0	1 0 0 1 1 0	DATA
1 0 1 1	1 0 0 0 1 1	DATA
1 1 0 0	1 1 0 1 0 0	DATA
1 1 0 1	1 1 0 0 0 1	DATA
1 1 1 0	1 1 0 0 1 0	DATA
1 1 1 1	1 0 1 0 0 1	DATA
	1 0 1 0 1 0	NIBBLE SYNC/END
	0 1 0 1 0 1	BIT SYNC
	1 1 1 0 0 0	UNUSED
	0 0 0 1 1 1	UNUSED

5 / 18

FIG_10






FIG. 11



SUBSTITUTE SHEET

6/18



SUBSTITUTE SHEET

7/18





FIG. 18

SUBSTITUTE SHEET


8/18

FIG 14


3-OF-6 ENCODE

**FIG 15**


3-OF-6 DECODE



9/18

FIG 16

10/18




SUBSTITUTE SHEET


11/18

FIG 18

I/O COUNTING TIMING



12/18



13/18

FIG. 20




FIG 21

(D TO A)






FIG. 22

(A T O D)





15/18

FIG 24
CONTENTION & I/O STATE DIAGRAM







FIG 25
LINK LEVEL ARQ STATE DIAGRAM





SUBSTITUTE SHEET

16/18

FIG 26PRIMARY STATION CONNECTION
STATE DIAGRAM**FIG 27**SECONDARY STATION CONNECTION
STATE DIAGRAM

SUBSTITUTE SHEET

17/18

FIG 28 GROUPING DEVICE**FIG 29**


18/18

FIG 30

SHARED RESOURCES

RESOURCE	RAM WORDS (DESIGNATED RAM LOCATIONS)
EEPROM	IDLE, PROC 1, PROC 2, PROC 3, PROC 4
I/O #1	IDLE, PROC 1, PROC 2, PROC 3, PROC 4
I/O #2	IDLE, PROC 1, PROC 2, PROC 3, PROC 4
I/O #3	IDLE, PROC 1, PROC 2, PROC 3, PROC 4
I/O #4	IDLE, PROC 1, PROC 2, PROC 3, PROC 4

ONE OF 5 STATES STORED



INTERNATIONAL SEARCH REPORT

International Application No. PCT/US88/02390

I. CLASSIFICATION OF SUBJECT MATTER (if several classification symbols apply, indicate all) ⁶		
According to International Patent Classification (IPC) or to both National Classification and IPC		
INT. CL ⁴ H04Q 3/00		
U.S. CL. 340/825.53; 370/94, 100		
II. FIELDS SEARCHED		
Minimum Documentation Searched ⁷		
Classification System	Classification Symbols	
U.S.	371/52 340/825.53, 825.52, 825.5, 825.51 370/92, 94, 60, 85, 100	
Documentation Searched other than Minimum Documentation to the Extent that such Documents are Included in the Fields Searched ⁸		
III. DOCUMENTS CONSIDERED TO BE RELEVANT ⁹		
Category *	Citation of Document, ¹¹ with indication, where appropriate, of the relevant passages ¹²	Relevant to Claim No. ¹³
A, E	US, A, 4,761,646 (CHOQUET ET AL) 02 August 1988	1-3,7-14,24-30
A	US, A, 4,131,881 (ROBINSON) 26 December 1978	1-3,7-14,24-30
A	US, A, 3,699,523 (PERCHER) 17 October 1972	1-3,7-14,24-30
A	US, A, 4,535,450 (TAN) 13 August 1985	1-3,7-14,24-30
Y, P	US, A, 4,745,593 (STEWART) 17 May 1988 (Note column 3, lines 22-24 for cell ID added to a packet)	4-6,31-35, 36-40,41-45
Y	US, A, 4,706,080 (SINCOSKIE) 10 November 1987 (Note column 5, lines 15-25 for cells grouped in a spanning tree)	46,47
Y	US, A, 4,594,708 (SERVEL ET AL) 10 June 1986 (Note column 3, lines 29-63 for synchronization)	48-50
Y, P	US, A, 4,736,409 (HASEGAWA ET AL) 05 April 1988 (Note Figure 1 for plural processors)	15-23
(CONTINUED)		
<p>* Special categories of cited documents: ¹⁰</p> <p>"A" document defining the general state of the art which is not considered to be of particular relevance</p> <p>"E" earlier document but published on or after the International filing date</p> <p>"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)</p> <p>"O" document referring to an oral disclosure, use, exhibition or other means</p> <p>"P" document published prior to the international filing date but later than the priority date claimed</p> <p>"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention</p> <p>"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step</p> <p>"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.</p> <p>"Δ" document member of the same patent family</p>		
IV. CERTIFICATION		
Date of the Actual Completion of the International Search	Date of Mailing of this International Search Report	
25 APRIL 1989	05 MAY 1989	
International Searching Authority	Signature of Authorized Officer	
ISA/US	Douglas W. Olms	

FURTHER INFORMATION CONTINUED FROM THE SECOND SHEET

Y	IEEE Transactions on computers, Vol. C-22, No. 3, March 1973, ANDERSON and METZE, "Design of Totally Self-Checking Check Circuits For m-out-of-n-Codes" Pages 263 to 269 (Note Page 268)	31-45, 48-50
---	--	--------------

V. ☐ OBSERVATIONS WHERE CERTAIN CLAIMS WERE FOUND UNSEARCHABLE¹

This international search report has not been established in respect of certain claims under Article 17(2) (a) for the following reasons:

1. ☐ Claim numbers _____, because they relate to subject matter¹² not required to be searched by this Authority, namely:

2. ☐ Claim numbers _____, because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out¹³, specifically:

3. ☐ Claim numbers _____, because they are dependent claims not drafted in accordance with the second and third sentences of PCT Rule 6.4(a).

VI. ☒ OBSERVATIONS WHERE UNITY OF INVENTION IS LACKING²

This International Searching Authority found multiple inventions in this international application as follows:

- I. Claims 1-3, 7-14 and 24-30 drawn to addressed communication system
- II. Claims 4-6, 31-40, 46, 47 drawn to packetized communication system
- III. Claims 15-23 drawn to communication cell with multiple processors
- IV. Claims 41-45, 48-50 drawn to cell with synchronizing circuit

1. ☒ As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims of the international application.

2. ☐ As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims of the international application for which fees were paid, specifically claims:

3. ☐ No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claim numbers:

4. ☐ As all searchable claims could be searched without effort justifying an additional fee, the International Searching Authority did not invite payment of any additional fee.

Remark on Protest

- ☐ The additional search fees were accompanied by applicant's protest.
- ☐ No protest accompanied the payment of additional search fees.

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER: _____**

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.